

โปรดอ่านคู่มืออย่างระมัดระวัง

โทรศัพท์สนับสนุนการโทรแบบสองซิมการ์ด แทนที่คุณต้องมีโทรศัพท์สองเครื่องเวลาเดียวกันลดปัญหาที่แท้จริง สนุกกับชีวิตของวิทยาศาสตร์และเทคโนโลยีได้ การออกแบบหน้าจอโทรศัพท์ถูกออกแบบมาเพื่อใช้กับ GSM / เครือข่าย GPRS พร้อมด้วยฟังก์ชันการสื่อสารขั้นพื้นฐานก็ยังมีหน้าที่ปฏิบัติเพื่อช่วยงานและชีวิตของคุณเช่น การเข้าภาษาอังกฤษการใช้ปากกา สมุดโทรศัพท์, 64 เสียงเรียกเข้า, นาฬิกา / นาฬิกาปลุก ปฏิทิน, การจัดสุภาพ, เครื่องคิดเลข, เกมส์, Bluetooth, ทีวี, วิทยุ FM, บันทึกภาพยนตร์ที่มีประสิทธิภาพ, MP3 และ MP4 เล่นและการ์ดหน่วยความจำ นอกจากนี้โทรศัพท์นี้ได้พัฒนาโปรแกรมที่มีอินเตอร์เฟซส่วนบุคคลและมีการออกแบบการทำงานเพื่อสนองความต้องการของแต่ละบุคคลอย่างดี

สารบัญ

บทที่ 1 ข้อมูลความปลอดภัย	5
1.1 การป้องกันทั่วไป	5
1.2 การป้องกันแบคเตอรี	6
1.3 การป้องกันการชาร์จ	7
บทที่ 2 ข้อเสนอแนะการใช้โทรศัพท์	9
2.1 ซิมการ์ด	9
2.2 แบคเตอรี	10
2.3 สายคาด้ำ	11
2.4 การเปิด/ปิด	12
บทที่ 3 รายละเอียดเมนู	12
3.1 สมุดโทรศัพท์	12
3.2 ข้อความ	15
3.3 ศูนย์รวมการโทร	22

3.4 การตั้งค่างาน	28
3.5 มัลติมีเดีย	36
3.6 การจัดการไฟล์	42
3.7 สุนุกและเกม	44
3.8 โพรไฟล์ผู้ใช้	44
3.9 จัดงาน ORGANIZER	46
3.10 การบริการ	49
3.11 เพิ่มเติม	54
3.12 เมนูลัด	58
บทที่ 4 การแก้ปัญหา	59

CHAPTER 1 SAFETY INFORMATION	60
1.1 GENERAL PRECAUTIONS	60
1.2 BATTERY PRECAUTIONS	61
1.3 CHARGER PRECAUTIONS	62
CHAPTER 2 PHONE INTRODUCTION	64
2.1 SIM CARD	64
2.2 BATTERY	64
2.3 DATA LINE	66
2.4 POWER ON/OFF	66
CHAPTER 3 MENU DETAILS	67
3.1 PHONEBOOK	67
3.2 MESSAGES	69
3.3 CALL CENTER	75
3.4 SETTINGS	80
3.5 MULTIMEDIA	85
3.6 FILE MANAGER	89
3.7 FUN & GAMES	90
3.8 USER PROFILES	91
3.9 ORGANIZER	92
3.10 SERVICES	94
3.11 EXTRA	97
3.12 SHORTCUTS	100
Chapter 4 Troubleshooting	101

บทที่ 1 ข้อมูลความปลอดภัย

1.1 การป้องกันทั่วไป

- โปรดปิดโทรทัศน์ของคุณในเครื่องบินโรงพยาบาลหรือพื้นที่ที่โทรทัศน์อาจรบกวนการทำงานของอุปกรณ์ที่สำคัญหรือแพทย์
- เพื่อป้องกันการรบกวนของคลื่นวิทยุจากสาเหตุผิดปกติหรือปัญหาอื่น ๆ ที่ไม่ได้ใช้โทรทัศน์ของรบบสัญญาณอ่อนสูงถูกต้องหรืออุปกรณ์อิเล็กทรอนิกส์ โดยเฉพาะเครื่องกระตุ้นหรืออุปกรณ์ทางการแพทย์อื่น ๆ ตรวจไฟ้อัดโนมิติควบคุมประตู่และอุปกรณ์.
- ไม่เคาะ, เขย่าหรือโยนโทรทัศน์จะทำให้โทรทัศน์จะพังพินาศหรือทำให้เกิดเพลิงไหม้ได้
- ไม่ใส่แบตเตอรี่โทรทัศน์หรือชาร์ตเข้าเตาไมโครเวฟหรือเครื่องแรงสูงอื่น ๆ โทรทัศน์อาจพังได้
- ไม่วางเครื่องในบริเวณที่มีอุณหภูมิสูงความชื้นสูงหรือกับอากาศที่มีฝุ่น โทรทัศน์จะพังได้
- ให้โทรทัศน์ออกจากกรเข้าถึงของเด็ก ซึ่งเด็กอาจใช้เป็นของเล่นและบาดเจ็บได้
- ไม่วางโทรทัศน์บนโต๊ะไม่เรียบหรือไม่มั่นคง โทรทัศน์อาจตกและแตกได้
- ห้ามรีดหรือซ่อมโทรทัศน์เอง โทรทัศน์จะพังหรือทำให้เกิดไฟฟ้ารั่วหรือปัญหาอื่น ๆ ได้
- ไม่ใช้เข็มหรือปากกาหรือชี้วัตถุอื่น ๆ กดคีย์นั้นโทรทัศน์อื่นอาจทำลายลงและผิดปกติ
- **ป้องกันโทรทัศน์จากใกล้วัตถุแม่เหล็กเช่นบัตรแม่เหล็กบัตรเครดิตฟลิปปีดิสก์** คลื่นวิทยุของโทรทัศน์อาจจะลบข้อมูลที่เก็บไว้ในพวกเขา
- ไม่เปิดเผยโทรทัศน์ให้ความชื้นน้ำหรือของเหลวอื่น ๆ อื่น ๆ โทรทัศน์อาจพังพินาศ.
- เพื่อป้องกันอุบัติเหตุจรรยาจรไม่ต้องใช้โทรทัศน์ขณะขับรถ
- ให้ใช้แบตเตอรี่และเครื่องชาร์จแบตเตอรี่ได้รับมอบอำนาจจากผู้ผลิตเท่านั้น เพราะยี่ห้ออื่น ๆ อาจทำให้เกิดการรั่วไหลความร้อนมากเกินไประเบิดได้

กรุณาอ่านและทำความเข้าใจคู่มือเล่มอย่างระมัดระวัง

1.2 การป้องกันแบคทีเรีย

- ไมโยนแบคทีเรียลงในกองไฟ เพราะอาจไฟไหม้เกิดขึ้น
- เวลาไม่ใช่บังคับให้ถอดแบคทีเรีย เพื่อไม่ให้แบคทีเรียรั่วหรือร้อนมากเกินไปจนระเบิดและไฟไหม้อาจเกิดขึ้น.
- ระวังการลัดวงจรกับแบคทีเรีย กรณีใส่พร้อมกับวัตถุโลหะคล้ายเส้นเข็มและสร้อยคอ และถ้ามีความร้อนมากเกินไปจะระเบิดและไฟไหม้อาจเกิดขึ้น.
- ห้ามซ่อมหรือถอด แบคทีเรียหรือประสานจุดรั่วไหลทำให้เกิดความร้อนมากเกินไประเบิดและไฟไหม้อาจเกิดขึ้น.
- ของเหลวจากแบคทีเรียอาจทำให้ตาบอดหากเข้าตามนุษย์ หากเกิดกรณีนี้โปรดล้างตาด้วยน้ำสะอาดทันที (ไม่ถูตา) และไปที่โรงพยาบาลโดยเร็วที่สุด.
- ห้ามวางโทรศัพท์ใกล้พื้นที่ของอุณหภูมิสูงเช่นไฟ ความร้อนมากเกินไประเบิดและไฟไหม้อาจเกิดขึ้น.
- หากแบคทีเรีย ร้อนขึ้นการเปลี่ยนสีหรือการบิดเบือน จากการใช้งานให้หยุดใช้และเปลี่ยนใหม่ทันที
- ถ้าเหลวที่รั่วจากแบคทีเรียโดนผิวหนังหรือเสื้อผ้าจะทำให้สามารถเผาไหม้ได้ ให้ล้างผิวหนังหรือเสื้อผ้าด้วยน้ำหรือไปโรงพยาบาลเมื่อจำเป็น.
- หากการรั่วของแบคทีเรียหรือมีกลิ่นผิดปกติ ให้ถอดแบคทีเรียออกทันที เพราะความร้อนมากเกินไปอาจจะเกิดระเบิดและไฟไหม้ขึ้น.
- ป้องกันแบคทีเรียจากความชื้นความร้อนมากเกินไป อาจเกิดเป็นไอและการกัด

กร่อนวัสดุอื่นได้

- ห้ามไม่ให้ใส่แบตเตอรี่ได้แสงแดดโดยตรงหรือพื้นที่ใกล้ของอุณหภูมิสูงเช่นรถยนต์; มิฉะนั้นอาจทำให้เกิดการรั่วไหลและความร้อนมากเกินไปรวมทั้งมีผลต่อประสิทธิภาพของแบตเตอรี่และลดช่วงชีวิตแบตเตอรี่
- อย่าชาร์จแบตเตอรี่เกินกว่า 24 ชั่วโมง
- แบตเตอรี่มีอายุจำกัดและจะลดลงหลังจากที่ชาร์จไฟบ่อยๆ ถ้าไม่ทำงานหลังจากชาร์จไฟบ่อยๆ แสดงว่าจบชีวิตของแบตเตอรี่ คุณต้องแทนที่ด้วยแบตเตอรี่ใหม่ทันที
- ไม่ทิ้งของแบตเตอรี่กับขยะ ท่านควรทิ้งให้สอดคล้องกับกฎระเบียบ.

1.3 การป้องกันการชาร์จ

- ใช้ไฟ 220V AC มิฉะนั้นอาจทำให้เกิดการรั่วไหลความร้อนมากเกินไปและเกิดความเสียหายกับเครื่อง
- ห้ามทำลัดวงจรขณะชาร์จ ซึ่งอาจทำให้เกิดไฟฟ้าช็อก เป็นควันและความเสียหาย
- ห้ามใช้สายชาร์จที่ชำรุดหรือสายไฟที่เสีย มิฉะนั้นอาจทำให้เกิดไฟและไฟฟ้าช็อต
- ห้ามนำภาชนะที่มีน้ำใกล้ตัวชาร์จ ถ้าน้ำหกออกมาและเข้าไปในโทรศัพท์ จะทำให้เกิดความร้อนมากเกินไปไฟฟ้าวรั่วและปัญหาอื่นๆ
- ห้ามถอดหรือเชื่อมต่อตัวชาร์จด้วยตัวเอง อาจจะทำให้บาดเจ็บจากไฟฟ้าวรั่วและไฟไหม้ อาจเกิดขึ้น.
- ห้ามชาร์จในสถานที่ความชื้นสูงเช่นห้องน้ำจะทำให้ไฟฟ้าวรั่วหรืออัคคีภัยได้.

- ห้ามสัมผัสสายไฟหรือปลั๊กไฟไฟฟ้า ขณะที่มือเปียก ไฟฟ้าช็อตอาจเกิดขึ้น.
- ห้ามใส่วัตถุหนักทับสายไฟหรือซ่อม มิฉะนั้นไฟฟ้าอาจช็อตได้
- ถอดปลั๊กไฟทุกครั้งขณะการทำความสะดวกหรือบำรุงรักษาเครื่อง
- ถ้าคุณไม่ทำตามเนื้อหาของคู่มือนี้กับโทรศัพท์ของคุณ โทรศัพท์ของคุณจะไม่ทนทาน

บทที่ 2 ข้อแนะนำการใช้โทรศัพท์

2.1 ซิมการ์ด

ก่อนที่คุณจะใช้โทรศัพท์ของคุณคุณต้องใส่ซิม เป็นกุญแจเข้าไปในเครื่องข่าย GSM

ข้อมูลทั้งหมดที่เกี่ยวข้องกับการเชื่อมต่อกับเครือข่ายและล็อกการโทรที่ถูกรับบันทึกไว้ในบริเวณโลหะของซิม นอกจากนี้บันทึกในซิมชื่อและโทรในสมุดโทรศัพท์จะเป็น คุณยังสามารถนำซิมออกและใส่ลงในโทรศัพท์มือถือ GSM เครื่องอื่น (โทรศัพท์ใหม่จะอ่านซิมอัตโนมัติ)

เพื่อป้องกันการสูญเสียนและความเสียหายของข้อมูลที่เก็บไว้ในซิมพื้นที่โลหะของซิมไม่ควรสัมผัสและบัตรควรจะถูกเก็บในที่ไฟฟ้าและแม่เหล็ก เมื่อซิมเสียหายคุณจะไม่สามารถเข้าไปในเครื่องข่าย GSM ได้

TF (T - Flash) Card เป็นการ์ดหน่วยความจำแบบพกพาที่มีความจุขนาดใหญ่ สำหรับเก็บเพลงและไฟล์วิดีโอที่มีขนาดใหญ่กว่า หน่วยความจำของโทรศัพท์

* หมายเหตุ: เครื่องจะต้องปิดก่อนที่คุณจะถอดซิม หรือ TF card และห้ามใส่เมื่อโทรศัพท์อยู่ในการเชื่อมต่อกับแหล่งจ่ายไฟภายนอก จะทำให้ ซิมหรือ การ์ด อาจเสียหาย

- ก่อนติดตั้งซิม ต้องปิดโทรศัพท์และถอดแบตเตอรี่ออกเสมอ
- ใส่ซิมในช่องใส่ซิม และสไลด์แถบกลับ เพื่อล็อก
- เมื่อต้องการเอาซิมออก ให้ปิดโทรศัพท์เปิดฝาลัง ถอดแบตเตอรี่นั้นแล้วเปิดแถบล็อกซิมและถอดซิมออกจากสล๊อต.
- ก่อนติดตั้งการ์ดต้องปิดโทรศัพท์และถอดแบตเตอรี่ออกทุกครั้ง
- ใส่บัตรการ์ด ในช่องของการ์ด TF

- เมื่อต้องการถอดบัตรการ์ด TF ต้องปิดโทรศัพท์และนำการ์ด TF ออกจากสล็อต.

2.2 แบตเตอรี่

50% ของพลังงานแบตเตอรี่สามารถใช้ได้ในขั้นแรก หลังจากเอาออกมาใช้

การชาร์จครั้งแรก ต้องใช้เวลาอย่างน้อย 14 ชั่วโมง จะได้พลังงานเต็ม สำหรับครั้งแรกที่ชาร์จครั้งที่สองชาร์จแบตเตอรี่จนเต็ม จะได้พลังงานเต็มเช่นกัน และดำเนินการเช่นเดียวกันในครั้งที่สาม เพื่อเพิ่มประสิทธิภาพ

- การติดตั้งและถอดแบตเตอรี่

การถอดแบตเตอรี่ออกให้ดำเนินการดังต่อไปนี้:

1. 1. ถอดฝาแบตเตอรี่ออกโดยเลื่อนมัน
1. 2. ยกแบตเตอรี่ออกจากด้านหลังและเอามันออก

- การติดตั้งแบตเตอรี่ให้ดำเนินการดังต่อไปนี้:

1. 1. ล็อคแบตเตอรี่ลงในสล็อตแบตเตอรี่.
1. 2. ดันขึ้นจนกว่าจะถูกล็อกแน่นหนา.

- การชาร์จแบตเตอรี่

เสียบชาร์ตเข้าปลั๊กไฟ เมื่อแสงที่หลอดไฟติดก็เริ่มได้

เสียบตัวปลั๊กอีกข้างเข้าพอร์ตนด้านขวาของโทรศัพท์ สัญลักษณ์แบตเตอรี่ปรากฏที่มุมขวาด้านบนจะแสดงสถานะของการเริ่ม ถ้าโทรศัพท์ปิดระหว่างเรียกชาร์จ ภาพแสดงการชาร์จจะแสดงเป็นรูปถ่าน แสดงว่ามีความคืบหน้า ถ้าโทรศัพท์อยู่ในแบตเตอรี่ต่ำและมีการใช้สูงสุดเพียงอาจใช้เวลาระยะหนึ่งสำหรับการชาร์จ ไอคอนที่ปรากฏบนหน้าจอจึงจะเริ่ม เมื่อบาร์ชาร์จเต็ม

และคงที่ก็หมายถึงการชาร์จเสร็จสมบูรณ์ ถ้าโทรศัพท์ปิดระหว่างชาร์จ ภาพแสดงการชาร์จจะแสดงให้เห็นว่าเสร็จสมบูรณ์ กระบวนการนี้มักจะใช้เวลา 3 ~ 4 เป็นปกติว่าแบตเตอรี่โทรศัพท์ชาร์จอาจสร้างความร้อนบางส่วนระหว่างการชาร์จ เมื่อเสร็จแล้ว ให้ตัดการเชื่อมต่อจากโทรศัพท์จากไฟฟ้า

* หมายเหตุ: ห้ามถอดปลั๊กไฟเมื่อแบตเตอรี่ชาร์จ

- แบตเตอรี่จะต้องถูกเรียกเก็บกลับ จากบริษัทผู้ผลิตถ้าอุณหภูมิไม่อยู่ระหว่าง + 5 °C และ + 40 °C. แสดงว่าไม่ผ่าน อาจทำให้เกิดอันตราย
- การชาร์จแบตเตอรี่ควรเมื่อโทรศัพท์ถูกปิดโดยอัตโนมัติหรือแสดงค่าเตือนของแบตเตอรี่ต่ำ. หากแบตเตอรี่ยังไม่เคยขึ้นเวลาชาร์จจะสั้นลง
- เวลาสแตนด์บายและเวลาพูดคุยโดยผู้ผลิตมีการคำนวณในสภาพแวดล้อมที่เหมาะสม. เวลาจริงอาจแตกต่างกันกับสภาพเครือข่ายที่ทำงานและสภาพการทำงานโหมด.
- ให้แน่ใจว่าแบตเตอรี่มีการติดตั้งดีและสามารถชาร์จได้
- เมื่อชาร์จเสร็จแล้ว ควรตัดการเชื่อมต่อจากโทรศัพท์และแหล่งผลิตพลังงานไฟฟ้า
- ถ้าไม่ได้รับการตัดการเชื่อมต่อจากโทรศัพท์และพลังงานไฟฟ้า การทำงานจะเริ่มต้นอีกครั้งหลังจากพลังงานแบตเตอรี่ใช้ไป ในระยะ 5 ~ 8 ชั่วโมง ทั้งนี้ไม่นับเนื่องมาจากที่ทำให้เกิดผลร้ายในชีวิตของแบตเตอรี่

2.3 สาย Data

- ต่อสายเชื่อมต่อข้อมูลเมื่อโทรศัพท์ปิด ไอคอนหน้าเครื่องแสดงให้เห็นว่าโทรศัพท์

ปิด

- ต่อสายเชื่อมต่อข้อมูลเมื่อโทรศัพท์เปิดอยู่ จะมีเมนูจะปรากฏบนหน้าจอ
- การเก็บข้อมูล: ในโหมดที่เก็บเนื้อหาของโทรศัพท์สามารถเข้าถึงได้โดยใช้คอมพิวเตอร์.
- กล้อง Web: ในโหมดกล้องให้โทรศัพท์สามารถทำงานเป็นกล้องโดยใช้คอมพิวเตอร์.
- ชาร์จ : การใช้ฟังก์ชันนี้เพื่อการชาร์จเท่านั้น อุณหภูมิของโทรศัพท์จะยังคงเดิม

2.4 การเปิด - ปิด

- กดปุ่ม Power Key เพื่อเปิดโทรศัพท์หรือปิด
- ถ้าโทรศัพท์เปิดอยู่โดยไม่มีซิมข้อความของ "ใส่ซิม" จะปรากฏว่า The SIM card will be checked out after being inserted คือซิมจะถูกตรวจสอบว่าหลังจากใส่แล้วข้อมูลต่อไปนี้จะปรากฏบนหน้าจอว่า ใส่ PIN1 (ถ้าคุณได้กำหนดรหัสผ่านสำหรับซิม) ใส่รหัสผ่านของโทรศัพท์เคลื่อนที่ (ถ้าคุณตั้งรหัสผ่านสำหรับ unlocking โทรศัพท์).
- หลังจากที่คุณเชื่อมต่อระบบสำเร็จโทรศัพท์จะค้นหาเครือข่ายที่มี (แสดงบนหน้าจอ) เมื่อการเชื่อมต่อจะทำให้ไอคอนของจัดหาเครือข่ายจะปรากฏในศูนย์ของหน้าจอ ตอนนี้โทรศัพท์อยู่ในสถานะสแตนด์บายและพร้อมที่จะใช้.

* หมายเหตุ: ถ้า "หมายเลขฉุกเฉิน" จะปรากฏก็หมายความว่าคุณอยู่นอกพื้นที่ให้บริการของเครือข่าย แต่คุณยังสามารถโทรฉุกเฉินตามความแรงของสัญญาณของโทรศัพท์ของคุณ

บทที่3 รายละเอียดเมนู

3.1 สมุดโทรศัพท์

- Quick Search: ไปดูหน้าจอของสมุดโทรศัพท์ คุณสามารถป้อนข้อมูลที่ตรงกันในคอลัมน์เพื่อค้นหาด้านล่างโดยการเรียงลำดับรายการ โหมดการค้นหามีดังนี้ 1. อังกฤษ (กรณีที่ต่ำกว่า) 3. จำนวน กด IME Key เพื่อสลับระหว่างวิธีการป้อน.
 - SIM1 IP Dial: เปิดใช้งานการโทรแบบ IP dial-up ของหมายเลขในสมุดโทรศัพท์ โดย SIM1
 - SIM2 IP Dial: เปิดใช้งานการโทรแบบ IP dial-up ของหมายเลขในสมุดโทรศัพท์ โดย SIM2
 - Send SMS: ส่งข้อความไปยังหมายเลข
 - View: ตรวจสอบรายละเอียดของรายการ
 - Edit: แก้ไขรายการ
 - Delete: ลบรายการ
 - Duplicate: ซ้ำ: รายการสำรอง
 - Move: ย้าย: ย้ายเข้า
 - Copy: คัดลอกรายการ
 - ส่ง vCard
1. Send by SMS: โดยส่ง SMS: ส่งรายการผ่านทางข้อความ

2. Send by MMS: โดยส่ง MMS: ส่งรายการผ่านทางข้อความมัลติมีเดีย
 3. Send by Bluetooth: ส่งโดย Bluetooth: ส่งรายการผ่านทาง Bluetooth.
 4. Save to file: บันทึกไฟล์: บันทึกการเข้า
- Search contact: ติดต่อค้นหา: การค้นหาสมุดโทรศัพท์สำหรับรายการโดยชื่อ.
 - Add new contact: เพิ่มรายใหม่เพิ่มรายการใหม่เข้าสมุดโทรศัพท์ คุณสามารถจัดเก็บเข้าSIM1, SIM2 หรือโทรศัพท์


* หมายเหตุ: การทำงานจะแตกต่างกันในแง่ของรูปแบบการจัดเก็บ

- Copy All: สำเนาทั้งหมด: สำเนารายการทั้งหมดจากโทรศัพท์ไป บัตร1 บัตร 2; สำเนารายการทุกรูปแบบบัตรที่โทรศัพท์หรือคัดลอกรายการทั้งหมด จาก SIM1, SIM2 หรือในทางกลับกัน
- Delete: ลบ: เลือกรายการที่จะลบบันทึกโทร เลือกเพื่อลบบันทึกการโทรจาก SIM1, SIM2 ที่ละรายการ ส่วนDelete All: ลบบันทึกทั้งหมด โดยเลือกรายการที่จะลบจากการบันทึกโทร เลือกเพื่อลบบันทึกการโทรทั้งหมดจาก SIM1, SIM2หรือจากสมุดโทรศัพท์
- Calls Groups: กลุ่มการโทร โทรศัพท์สามารถแบ่งเป็นโปรแกรมที่มี 5 กลุ่มโทร คุณสามารถตั้งค่าสำหรับแต่ละกลุ่มแต่ละเช่นเปลี่ยนเสียงเรียกเข้า ภาพของกลุ่มที่โทรเข้ามาและการตั้งค่าส่วนตัวสมาชิกแต่ละกลุ่ม
- Extra Number: หมายเลขพิเศษเพิ่มเติม หรือหมายเลขอื่นๆเช่นโทรหมายเลขบริการและหมายเลขฉุกเฉินเก็บไว้ในซิม คุณสามารถตรวจสอบและแก้ไขหมายเลขอื่นๆเก็บไว้ในซิมได้

*หมายเหตุ: หมายเลขบริการต้องสนับสนุนโดยซิม

- Settings: ตั้งค่าสมุดโทรศัพท์ในสี่ประเภทหน่วยความจำตรวจสอบสถานที่เก็บในการ์ดหรือในสมุดโทรศัพท์
- Memory Check: หน่วยความจำตรวจสอบ สามารถตรวจสอบหน่วยความจำของซิมและโทรศัพท์.
- Storage Location: เลือกการเก็บรักษา เลือกตำแหน่งที่เก็บที่ต้องการโทรศัพท์หรือซิม.
- Card Setting: ตั้งค่าหรือการกำหนดเนื้อหาของรายการในสมุดโทรศัพท์.
- My Card: บัตรของฉัน แก๊ซและบันทึกข้อมูลรายละเอียดของผู้ใช้.
- Caller picture: ภาพของผู้โทร เลือกรูปภาพสำหรับสายเรียกเข้าแต่ละสาย
- Caller Ring tone: เลือกเสียงเรียกเข้าสำหรับสายเรียกที่เข้า
- Caller video: เลือกวิดีโอกับสายเรียกเข้า ภาพยนตร์ในโทรศัพท์หรือบันทึกโดยผู้ใช้สามารถระบุเป็นสำหรับวิดีโอของการโทรเข้ามาเมื่อมีการโทรมาวิดีโอจะกำหนดได้และจะเล่นตามที่กำหนด

3.2 ข้อความ

- ข้อความ
- Inbox  กล่องข้อความสามารถ เลือกได้ทั้ง SIM1 หรือ SIM2 ข้อความรับ เมื่อรายการข้อความ Inbox ปรากฏให้กดตกลงเพื่ออ่านข้อความ คุณสามารถเลือกตัวเลือกดังนี้

- Reply: ตอบ -: ตอบกลับผู้ส่งข้อความ.
 - Delete: ลบ: ลบข้อความ.
 - Edit: แก้ไข: แก้ไขข้อความ.
 - Forward: ส่งต่อ: ส่งข้อความ
 - Copy to SIM Card (Phone): คัดลอกไปซิมการ์ด (โทรศัพท์): สำเนาข้อความจากโทรศัพท์ในซิมหรือในทางกลับกัน.
 - Move to SIM Card (Phone): ย้ายไปที่ซิมการ์ด (โทรศัพท์): ย้ายข้อความจากเครื่องไปซิมหรือในทางกลับกัน.
 - Chat: สนทนา: ใส่ไว้ในห้องสนทนา.
 - Delete All: ลบทั้งหมด: ลบข้อความทั้งหมดในกล่องจดหมาย
 - Copy All: สำเนาทั้งหมด: คัดลอกทุกข้อความจากซิมการ์ดไปยังโทรศัพท์หรือจากโทรศัพท์ไปยังซิม.
 - Move All: ย้ายทั้งหมด: ย้ายข้อความทั้งหมดจากซิมการ์ดไปยังโทรศัพท์หรือจากโทรศัพท์ไปยังซิม.
 - Use Number: ใช้หมายเลขโทรหรือเก็บในสมุดโทรศัพท์หมายเลขสกัดจากข้อความ.
 - Use Link: ลิงค์ใช้การกระจายและเก็บลิงค์เว็บที่อยู่ในข้อความ.
- Outbox: กล่องขาออก: สามารถเลือกกล่องขาออก SIM1 หรือ SIM2 กล่องขาออกยกเลิกการตรวจสอบแบบส่งข้อความ เมื่อตรวจสอบรายชื่อข้อความขาด

ออก, ยืนยันกดเพื่ออ่านข้อความ คุณสามารถเลือกตัวเลือกดังนี้

- Send form SIM1: ส่งข้อความจากแบบฟอร์ม SIM1 คุณสามารถส่งจาก SIM1 แบบข้อความมากกว่าหนึ่งและถึงผู้รับโดยเลือกส่งถึงผู้รับหลายรายหรือกลุ่ม.
- Send form SIM2: ส่งข้อความจากแบบฟอร์ม SIM2 คุณสามารถส่งจาก SIM2 แบบข้อความมากกว่าหนึ่งและถึงผู้รับโดยเลือกส่งถึงผู้รับหลายรายหรือกลุ่ม.
- Edit: แก้ไข: แก้ไขข้อความ.
- Delete: ลบ: ลบข้อความ.
- Copy to SIM Card (Copy to Phone): คัดลอกไป SIM Card (คัดลอกไปยังโทรศัพท์): สำเนาข้อความจากโทรศัพท์ในซิมหรือในทางกลับกัน.
- Move to SIM Card (Move to Phone): ไปที่ SIM Card (ย้ายไปที่โทรศัพท์): ย้ายข้อความจากเครื่องไปซิมหรือในทางกลับกัน.
- Delete All: ลบทั้งหมด: ลบข้อความในถาดออก
- Copy All: สำเนาทั้งหมด: คัดลอกจากซิมการ์ดไปยังโทรศัพท์หรือจากโทรศัพท์ไปยังซิม
- Move All: ย้ายทั้งหมด: ย้ายจากซิมการ์ดไปยังโทรศัพท์หรือจากโทรศัพท์ไปยังซิม
- Use Number: ใช้หมายเลขโทรหรือเก็บในสมุดโทรศัพท์หมายเลขถัดจากข้อความ
- Use Link: ลิงค์ให้: Extract และเก็บลิงค์เว็บที่อยู่ในข้อความ

- Write message | ข้อความ เขียน: ป้อนในการเขียนข้อความ คุณสามารถส่งข้อความสั้นๆ

- Complete: เลือกรายการที่จะยื่นในการสิ้นสุดข้อความและคุณสามารถใช้ขั้นตอนถัดไป.

1. ส่งเท่านั้น: ส่งข้อความให้เลือกที่จะได้เป็นผู้รับและคุณสามารถป้อนหมายเลขโทรศัพท์หรือดูจากสมุดโทรศัพท์และเลือกหมายเลขโทรศัพท์แล้วรับ ป้อนแล้วยืนยันการส่ง.
2. ส่งและบันทึก: ในขณะที่ส่งข้อความนั้นจะบันทึกโดยอัตโนมัติในกล่องขาออก.
3. บันทึก: ไม่ส่งข้อความแต่เพียงบันทึกลงในถาดออก
4. ส่งให้หลายข้อความไปยังหมายเลขโทรศัพท์หลายหมายเลข
5. ส่งในกลุ่ม: เลือกกลุ่มและส่งข้อความไปยังสมาชิกทุกคนในกลุ่ม.

- Templates : แม่แบบ: แม่แบบใส่ข้อความลงในข้อความ.
- Insert object: ใส่ภาพใส่เสียงเสียงเรียกเข้า, การ์ตูนและเพลงเริ่มต้นกับข้อความ.
- Text format: รูปแบบข้อความ: กำหนดรูปแบบการแก้ไขข้อความ.
- Insert number: ใส่หมายเลข: เพิ่มหมายเลขจากสมุดโทรศัพท์.
- Insert contact: ใส่ผู้ติดต่อเพิ่ม เพิ่มชื่อจากสมุดโทรศัพท์
- Input method: วิธี Input: การเปลี่ยนแปลงวิธีการป้อนข้อมูล.

*หมายเหตุ: บางเมืองและศูนย์ข้อความสนับสนุนข้อความไม่เกิน 70 ตัวอักษร (หรือ 160 ข้อความภาษาอังกฤษ)

- Templates:: ประโยคที่ใช้บ่อยได้ถูกบันทึกไว้ที่นี่เพื่อหลีกเลี่ยงการเขียนใหม่ได้ในระหว่างการแก้ไขข้อความ จะแก้ไขได้และสามารถลบได้
- Message setting: การตั้งค่าข้อความ: ก่อนที่จะใช้งานข้อความคุณต้องตั้งค่าที่จำเป็น.
- Profile settings: การตั้งค่า Profile: กำหนดโหมดที่เหมาะสมสำหรับข้อความมือถือคือ ไปในแต่ละโหมดเพื่อค้นหาชื่อที่ตรงกับหมายเลขศูนย์ข้อความตรวจสอบเวลาการส่งการตั้งค่าโปรไฟล์.
- Common settings: การตั้งค่าทั่วไป: เปิดใช้งานรายงานหรือตอบทาง.
- Memory status: สถานะหน่วยความจำตรวจสอบพื้นที่ว่างในซิมหรือกล่องข้อความมือถือ.
- Preferred storage: เก็บต้องการ: เลือกที่จะบันทึกในบัตรโทรศัพท์มือถือหรือซิม.
- **ข้อความมัลติมีเดียมีข้อความ**

MMS (Multimedia Messaging Service) ข้อความมัลติมีเดียมีข้อความและภาพ คุณสามารถไม่เพียงส่งหรือรับรูปภาพและข้อความแต่ยังได้รับไฟล์เสียงที่แนบมากับข้อความโทรศัพท์ สนับสนุนข้อความมัลติมีเดียที่มีหลายหน้าคือแต่ละหน้าประกอบด้วยหนึ่งภาพหนึ่งซันดนตรี และข้อความมัลติมีเดียที่มีหลายหน้า ขนาดของรูปภาพในข้อความมัลติมีเดียจะถูกปรับโดยอัตโนมัติเพื่อให้หน้าจอของโทรศัพท์.

*หมายเหตุ: ฟังก์ชันนี้ต้องการการสนับสนุนของยูเอชดีเอชเอ.

- Write a Message: เขียนข้อความ: สร้างข้อความมัลติมีเดียใหม่ คุณต้องกรอกผู้รับคัดลอกสำเนาฉบับเนื้อหาวิชาและเอกสารแนบ.

- Inbox: กล่องข้อความมัลติมีเดียที่ได้รับ (คล้ายกับกล่องจดหมายของข้อความ.)
 - Read: อ่าน: อ่านข้อความมัลติมีเดีย.
- Details: รายละเอียด: ตรวจสอบรายละเอียดของข้อความมัลติมีเดียรวมทั้งเรื่อง
วันเวลาและ ขนาด
- Use number: หมายเลขใช้: สารสกัดจากจำนวนผู้ส่ง.
- Reply: ตอบ: ตอบในรูปแบบมัลติมีเดียที่ผู้ส่งของข้อความมัลติมีเดียหรือผู้ส่ง
ทั้งหมดและผู้รับ
- Reply: ตอบ: ตอบในการส่งข้อความของผู้ส่งข้อความมัลติมีเดียหรือทั้งหมดและ
ผู้รับ
 - Forward: ส่งต่อ: ส่งข้อความมัลติมีเดียอื่น.
 - Receive: การรับได้รับหากข้อความมัลติมีเดียไม่ได้รับ, ได้รับ.
 - Disconnect ปลด: ตัดการเชื่อมต่อ กับ GPRS.
 - Delete: ลบ: ลบข้อความมัลติมีเดีย.
 - Delete All: ลบทั้งหมด: ลบข้อความมัลติมีเดียในกล่องจดหมาย.
- Outbox: กล่องขาออก: เก็บข้อความมัลติมีเดียที่ส่งไม่สำเร็จไม่สำเร็จ.
- Drafts: ร่าง: เก็บข้อความมัลติมีเดียไม่ได้ตั้งใจที่จะส่ง.
- Templates: แม่แบบ: ประโยคที่ใส่บ่อยได้ถูกบันทึกไว้ที่นี่เพื่อหลีกเลี่ยงการเขียน
ใหม่ได้ในระหว่างการแก้ไขข้อความจะแก้ไขได้และสามารถลบ.

- MMS Setting: MMS การตั้ง: ตั้งค่าพารามิเตอร์ของการส่งและรับข้อความมัลติมีเดีย.
- Profiles Setting: โปรไฟล์ตั้ง: การตั้งค่า MMS รวมถึงการตั้งค่าของศูนย์ MMS, เชื่อมโยงพิมพ์ gateway, พอร์ตและบัญชี.

*หมายเหตุ: การตั้งค่า MMS ต้องตั้งค่าตามที่จัดหาเครือข่ายท้องถิ่นของมาตรฐานเช่นการเชื่อมโยงประเภทเลือกเป็น WAP หรือ HTTP.

- แก๊ไขการตั้ง: ตั้งค่าพารามิเตอร์ของการแก้ไขข้อความมัลติมีเดียเช่นโหมดแก้ไขภาพย่อ, ไลเซนเป็นต้น.

- Send Setting: ส่งตั้ง: ตั้งค่าพารามิเตอร์ของการส่งข้อความมัลติมีเดียเช่นระยะเวลาส่งรายงานอ่านรายงาน Priority เวลาช่วงระยะหยุดพักและเวลาที่ส่ง
- Receive Setting: ได้รับการตั้ง: ตั้งค่าพารามิเตอร์ที่ได้รับข้อความมัลติมีเดียเช่นเครือข่ายหลักโรมมิ่งเครือข่ายส่งรายงานรายงานอ่านและอนุญาตให้ส่งรายงานเป็นต้น.
- Filter:ตัวกรอง:
- Memory: พื้นที่ของความจำและการบันทึกข้อความมัลติมีเดียที่ใช้หน่วยความจำและหน่วยความจำฟรี.
- Chat สนทนา

หน้าที่ของห้องสนทนามีดังนี้

- Chat Room info: แชทข้อมูลห้อง: ใส่ชื่อเล่นและจำนวนคู่ของคุณ

- Start new: เริ่มข้อความเข้าใหม่
- Voicemail server ข้อความเสียง

หน้าที่ของกล่องเสียงมีดังนี้

- แก๊ไข: คุณสามารถกำหนดชื่อและหมายเลขโทรศัพท์.
- เชื่อมต่อกับกล่องจดหมายเสียงเพื่อฟังข้อความเสียงที่คุณกำหนด
- การกระจายข้อความแบบออกอากาศ

หน้าที่ของการรับและอ่านข้อความที่ออกอากาศมีดังนี้

- Receiving Mode: การรับ : เปิดหรือปิดรับข้อความออกอากาศ
- Read Message: การอ่านข้อความ: อ่านข้อความออกอากาศที่คุณต้องการ
- Language: ภาษา: ตั้งภาษาของออกอากาศ
- Channel Setting: ช่องตั้ง: ตั้งช่องทางในการออกอากาศเซลล์รวมทั้งเลือกเพิ่มแก๊ไขและลบ

3.3 ศูนย์รวมการโทร

- Call history ประวัติการโทร

คุณสามารถเลือกประวัติสาย SIM1 หรือประวัติการโทร SIM2, ดังนี้

- Missed Calls: พลาดสาย: ใช้บันทึก 20 พลาดสาย
- Dialed Calls: สายที่โทรออก : ใช้บันทึกการโทร 20 สายที่โทรออก

- Received Calls: สายที่ได้รับ: เพื่อใช้บันทึก 20 สายที่ได้รับ.

ในรายการบันทึก, ตกลงกดเพื่อตรวจสอบรายละเอียดของรายการเช่นวันที่เวลาชื่อ (ถ้าบันทึกในสมุดโทรศัพท์) จำนวนและเวลาของการโทร.

ในรายละเอียดของรายการตัวเลือกกดเพื่อดำเนินการต่อไปนี้

- IP Dial-up: เปิดใช้งาน IP dial-up ของตัวเลขในการบันทึก
- Send message: ข้อความส่ง: ส่งข้อความไปยังหมายเลข
- Send MMS: ส่ง MMS: ส่งข้อความ MMS ให้เขาจำนวน
- Delete all ลบ: ลบบันทึกทั้งหมด
- Delete: ลบ: ลบรายการ.
- Save: บันทึก: บันทึกรายการในซิมหรือโทรศัพท์.
- Dial: โทร: การโทร
- Edit: แก้ไข: แก้ไขรายการและเพิ่มลงในสมุดโทรศัพท์.
- Delete Log: ลบรายการการโทร: ผู้ใช้สามารถเลือกการลบรายการทั้งหมดของรายการ.
- Call Duration: ระยะเวลาการโทร: ย่อยสีเมนูให้โนโทรออก ระยะเวลาการโทรครั้งสุดท้าย, การโทรที่ผ่านไปแล้ว, การโทรที่ได้รับสายและการเคลียทั้งหมด
- Last Call: การโทรครั้งสุดท้าย: ตรวจสอบระยะเวลาโทรสุดท้าย.
- Dialed Calls: สายที่โทรไปแล้ว: ตรวจสอบระยะเวลาของสายที่โทรไปแล้ว

- Received Calls: สายที่ได้รับ: ตรวจสอบระยะเวลารวมของการเรียกได้รับ.
- Clear All: ล้างทั้งหมด: จับเวลาชัดเจนและเริ่มนับ.
- Call time □ เวลา โทร: ช่วงเวลาที่สามารถเก็บข้อมูลการคิดค่าโทรของคุณทั้งหมด.
- Last Call Charge: การคิดค่าการโทรครั้งสุดท้าย: ตรวจสอบค่าโทรล่าสุด.
- All Call Charger □ การคิดค่าโทร ทั้งหมด : ตรวจสอบค่าโทรทั้งหมด.
- Reset Call Meter: รีเซ็ต Call Meter: ใส่รหัส PIN2 เพื่อรีเซ็ตเมตรโทร.
- Charge Limitation: จำกัดค่าการโทร: ป้อนลงในเมนูย่อยนี้และที่สำคัญในรหัส PIN2 เพื่อดูแก้ไขหรือยกเลิกฟังก์ชัน.
- Price and Rate: ราคาและอัตรา: ใส่ลงในเมนูย่อยนี้เพื่อเรียกดูแก้ไขหรือยกเลิกการใช้งานที่หลังสองหน้าที่ต้องใส่รหัส PIN2.

*หมายเหตุ: การดำเนินงานบางอย่างต้องใช้รหัส PIN2; โปรดติดต่อจัดหาเครือข่ายของคุณ

*หมายเหตุ: การสนับสนุนเครือข่ายจำเป็น

● การนับข้อความ

- Sent: ส่ง: บันทึกหมายเลขของข้อความที่ส่ง.
- Received: รับ: บันทึกหมายเลขของข้อความที่ได้รับ.

กด Soft Key ทางซ้ายของ "ตั้งค่า" เพื่อยกเลิกสองรายการข้างต้น

● การนับ GPRS

- Last Sent: ส่งครั้งสุดท้าย: บันทึกไปครั้งที่ส่งครั้งสุดท้าย.
- Last received: ล่าสุดได้รับ: bytes บันทึกที่ได้รับครั้งสุดท้าย.
- All Sent Data: ข้อมูลทั้งหมดที่ส่ง: บันทึก bytes ทั้งหมดที่ส่ง.
- All Received Data. ข้อมูลทั้งหมดที่ได้รับ: บันทึก bytes ทั้งหมดที่ได้รับ.
- Clear Counters: ลบการนับ: เริ่มต้น
- Call Settings การตั้งค่าการโทร
- SIM1 call settings การตั้งค่าการโทร SIM1

1 Caller ID แสดงหมายเลข

- Default: ค่าเริ่มต้น: การเริ่มต้น.โทรศัพท์ของคุณ
- Hide: ซ่อน: ด้านอื่น ๆ ไม่สามารถดูหมายเลขโทรศัพท์ของคุณระหว่าง (ต้องสนับสนุนการจัดหาเครือข่าย.)
- Send: ส่ง: ด้านอื่น ๆ สามารถดูหมายเลขโทรศัพท์ของคุณระหว่างโทร.

2 Call Waiting: สายเรียกซ้อน: คุณสามารถเปิดใช้งานจะแจ้งการเรียกเข้ามาขณะที่คุณกำลังโทร.

3 Call Diversion: การโอนสายการโทรไปหมายเลขอื่น

- Unconditional: ไม่มีเงื่อนไข: โทรเข้ามาไปยังหมายเลขอื่นโดยไม่มีเงื่อนไข.

- If Out of Reach: ถ้าวอกจากการเข้าถึง: การโทรเข้ามาไปยังหมายเลขอื่นถ้าคุณไม่สามารถโทร
- If Not Answered: หากไม่มีคำตอบ: โอนสายไปยังหมายเลขอื่น
- If Busy: ถ้าไม่ว่าง: โอนสายการโทรเข้ามาไปยังหมายเลขอื่นที่คุณตั้งไว้
- All Data Calls: ข้อมูลทั้งหมดของการโทรและการโอนสาย
- Cancel Diversion: ยกเลิกการโอนสาย

4 □ Call Barring: จำกัดการโทร

- Outgoing Calls: สายโทรออก: การจำกัดการโทร.
- Restrict Incoming Calls: จำกัดสายเรียกเข้า: จำกัดได้รับการเรียก
- Cancel Barring: ยกเลิกการจำกัด. (PIN2 ต้องการรหัส.)
- Change Password: เปลี่ยนรหัสผ่าน

5 □ การสลับระหว่างสาย 1 และสาย 2 (หมายเหตุ: เมื่อ สาย 2 ถูกเลือกเป็นค่าเริ่มจะไม่สามารถสลับสายได้)

6 □ การปิดกลุ่มผู้ใช้: ป้อนและเลือก "เพิ่ม" เพื่อป้อนชื่อใหม่ โดยใช้ปากกาสัมผัสเพื่อเลือกเสร็จสิ้นการ หลังจากนั้นใส่หมายเลขเนื้อหาและเลือกยืนยันการใช้ปากกา เลือกกลุ่มที่มีอยู่เพื่อแก้ไขเพิ่มใช้งานไม่ได้ใช้งานและลบ ปิดการตั้งค่ากลุ่มที่จะพิจารณาจากการจัดหาหรือตั้งค่า เฉพาะสมาชิกในกลุ่มได้เรียกกันเพื่อจำกัดค่าใช้จ่ายการโทร.

* หมายเหตุ: ฟังก์ชันความต้องการการสนับสนุนของผู้ใช้เครือข่ายของซิม

- การตั้งค่าการโทร SIM2

สามารถใช้เช่นเดียวกันกับการตั้งค่าการโทร SIM1.

- คุณสามารถเปิดและปิดเปลี่ยนแปลงเสียงการโทร.
- Close : ปิด: คุณสามารถเก็บเสียงไปตามปกติเมื่อคุณโทรปกติ
- Open: เปิด: เลือกเสียงของเด็ก ,ผู้หญิง,ผู้ชาย เบื่อและเสียงของคุณตั้งโทร
- การตั้งค่าล่วงหน้า

1 □ Black list □ รายชื่อที่ไม่ต้องการรับสาย : คุณสามารถแก้ไขหมายเลขโทรศัพท์ในรายการและเลือกที่จะเปิดหรือปิดการทำงาน ถ้าตั้งที่หมายเลขโทรศัพท์ในรายการจะปฏิเสธที่จะเชื่อมต่อ.

2 □ Automatic Redial: มีการโทรซ้ำของคุณ

3 □ Speed dial: การตั้งค่าหมายเลขที่จะโทรด่วน: กดปุ่มตัวเลขที่ตรงกับคดหมายเลขที่กำหนดไว้สำหรับพวกเขา.

4 □ IP Dial-up: การตั้งและจัดเก็บ IP dial-up ของหมายเลขในสมุดโทรศัพท์

5 □ Call time display: แสดงผลเวลา โทร: แสดงระยะเวลาการโทร

6 □ Call time reminder: เตือนเวลาโทร: แสดงระยะเวลาการโทร

7 □ Auto quick end: สิ้นสุดการโทรแบบด่วน: วางสายในขณะที่ตั้งค่า.

3.4 การตั้งค่า

- การตั้งค่า 2 ซิม

Dual SIM open: เปิด: เปิดใช้งาน 2ซิม

Only SIM1 เพียง SIM1 เปิดเท่านั้น SIM1

Only SIM2 เพียง SIM2 เปิดเท่านั้น SIM2

Flight mode: โหมดการบิน: ปิดเครือข่ายขณะทำการบิน.

- **การตั้งค่าปากกา**

คุณสามารถใช้หน้าจอสัมผัสได้ถูกต้อง

- **การตั้งค่าโทรศัพท์**

- Time and Date: เวลาและวันเวลาที่กำหนดและวันที่ของโทรศัพท์.
- Set home city เมืองบ้าน ตั้ง: ตั้งเมืองของคุณ
- Time/ Date Setting : เวลา / วันที่ตั้ง: ตั้งเวลาและวันที่ปัจจุบัน.
- Time Format: กำหนดรูปแบบการแสดงผลเวลา.
- Schedule power on/off: การกำหนดการเปิด / ปิด: ตั้งเวลาเมื่อโทรศัพท์เปิดและปิดโดยอัตโนมัติ.
- Language: ภาษา: ตั้งค่าภาษาสำหรับเมนู
- Preferred Input Method: เลือกวิธีการป้อนข้อมูลเริ่มต้น.
- **ลักษณะแสดง**
- Wallpaper: เลือกภาพพื้นหลัง

- Screen saver: โปรแกรมรักษาหน้าจอ: เลือกหน้าจอบันทึกภาพสำหรับสแตนด์และกำหนดเวลาที่รอ.
- Power on display: เลือกภาพเล่นเมื่อโทรศัพท์เปิด
- Power off display: เลือกภาพเล่นเมื่อโทรศัพท์ปิด.
- Date and Time Display. วันที่และเวลาแสดง: เปิดหรือปิดจอแสดงผลเวลาปัจจุบัน
- Greetings text: ข้อความทักทาย : เมื่อใช้งานเป็นข้อความที่แก้ไขจะปรากฏเมื่อโทรศัพท์เปิด
- Auto up date of data and time ชัตโนมิติการตั้งของข้อมูลวันและเวลา.
- Handwriting setting: การตั้งค่าลายมือ: ตั้งความเร็วคัดลายมือและเขียนสี.
- การตั้งค่า:
- LCD Backlight ตั้งค่า มือถือสว่าง และเวลาปิด.
- Keypad LED : เปิดและปิดแสงสว่างที่ปุ่มกด
- Keypad LED Style: สไตล์แสงสว่างและการตั้งค่ารูปแบบ LED.
- การตั้งค่าการโทร
- การตั้งค่าการโทร SIM1

1 Caller ID แสดงหมายเลข

- Default: ค่าเริ่มต้น: การเริ่มต้นโทรศัพท์ของคุณ
- Hide: ซ่อน: ด้านอื่นๆไม่สามารถดูหมายเลขโทรศัพท์ของคุณระหว่าง (ต้องสนับสนุนการจัดการเครือข่าย.)
- Send: ส่ง: ด้านอื่นๆสามารถดูหมายเลขโทรศัพท์ของคุณระหว่างโทร.

2 Call Waiting: สายเรียกซ้อน: คุณสามารถเปิดใช้งานจะแจ้งการเรียกเข้ามาขณะที่คุณกำลังโทร.

3 Call Diversion: การโอนสายการโทรไปหมายเลขอื่น

- Unconditional: ไม่มีเงื่อนไข: โทรเข้ามาไปยังหมายเลขอื่นโดยไม่มีเงื่อนไข.
- If Out of Reach: ถ้าออกจากการเข้าถึง: การโทรเข้ามาไปยังหมายเลขอื่นถ้าคุณไม่สามารถโทร
- If Not Answered: หากไม่มีคำตอบ: โอนสายไปยังหมายเลขอื่น
- If Busy: ถ้าไม่ว่าง: โอนสายการโทรเข้ามาไปยังหมายเลขอื่นที่คุณตั้งไว้
- All Data Calls: ข้อมูลทั้งหมดของการโทรและการโอนสาย
- Cancel Diversion: ยกเลิกการโอนสาย

4 Call Barring: จำกัดการโทร

- Outgoing Calls: สายโทรออก: การจำกัดการโทร.
- Restrict Incoming Calls: จำกัดสายเรียกเข้า: จำกัดได้รับการเรียก
- Cancel Barring: ยกเลิกการจำกัด. (PIN2 ต้องกรรหส์.)
- Change Password: เปลี่ยนรหัสผ่าน

5 □ การสลับระหว่างสาย 1 และสาย 2

(หมายเหตุ: เมื่อ สาย 2 ถูกเลือกเป็นค่าเริ่มจะไม่สามารถสลับสายได้)

6 □ การปิดกลุ่มผู้ใช้: ป้อนและเลือก "เพิ่ม" เพื่อป้อนชื่อใหม่ โดยใช้ปากกาสัมผัสเพื่อเลือกเสร็จสิ้นการ หลังจากนั้นใส่หมายเลขเนื้อหาและเลือกยืนยันการใช้ปากกา เลือกกลุ่มที่มีอยู่เพื่อแก้ไขเพิ่มใช้งานไม่ได้ใช้งานและลบ ปิดการตั้งค่ากลุ่มที่จะพิจารณาจากการจัดหาหรือตั้งค่า เฉพาะสมาชิกในกลุ่มได้เรียกกันเพื่อจำกัดค่าใช้จ่ายการโทร.

* หมายเหตุ: ฟังก์ชันความต้องการการสนับสนุนของผู้ใช้เครือข่ายของซิม

● การตั้งค่าการโทร SIM2

เดียวกันกับการตั้งค่าการโทร SIM1.

- คุณสามารถเปิดและปิดเปลี่ยนแปลงเสียงการโทร.
- Close : ปิด: คุณสามารถเก็บเสียงไปตามปกติเมื่อคุณโทรปกติ
- Open: เปิด: เลือกเสียงของเด็ก , ผู้หญิง, ผู้ชาย เมื่อและ คุณสามารถใช้เสียงของคุณตั้งโทร
- การตั้งค่าล่วงหน้า

1 ❑ Black list ❑ รายชื่อที่ไม่ต้องการรับสาย : คุณสามารถแก้ไขหมายเลขโทรศัพท์ในรายการและเลือกที่จะเปิดหรือปิดการทำงาน ถ้าตั้งที่หมายเลขโทรศัพท์ในรายการจะปฏิเสธที่จะเชื่อมต่อ.

2 ❑ Automatic Redial: มีการโทรซ้ำของคุณ

3 ❑ Speed dial: การตั้งค่าหมายเลขที่จะโทรด่วน: กดปุ่มตัวเลขที่ตรงกับกดหมายเลขที่กำหนดไว้สำหรับพวกเขา.

4 ❑ IP Dial-up: การตั้งและจัดเก็บ IP dial-up ของหมายเลขในสมุดโทรศัพท์

5 ❑ Call time display: แสดงผลเวลา โทร: แสดงระยะเวลาการโทร

6 ❑ Call time reminder: เตือนเวลาโทร: แสดงระยะเวลาการโทร

7 ❑ Auto quick end: สิ้นสุดการโทรแบบด่วน: วางสายในขณะที่ตั้งค่า.

- Network setup การติดตั้งเครือข่าย

แสดง SIM1 ตั้งค่าเครือข่ายและการตั้งค่าเครือข่าย SIM2

- เลือกเครือข่าย
 - Automatic: โดยอัตโนมัติ: ค้นหาโดยอัตโนมัติสำหรับเครือข่ายที่ซิมใช้งาน
 - Manual: คู่มือ: การค้นหาเครือข่ายทั้งหมดและลงทะเบียนด้วยตนเอง.
 - ต้องการเครือข่ายการเข้าเครือข่ายที่ต้องการด่วนตัวเอง

- การตั้งค่าการรักษาความปลอดภัย
- การตั้งค่าการรักษาความปลอดภัยซิม

1 การ ล็อค SIM1

- คุณสามารถตั้งค่าความปลอดภัยเพื่อป้องกันไม่ให้โทรศัพท์หรือซิมของคุณจากการใช้โดยผู้อื่นที่ไม่อนุญาต
- รหัส PIN สามารถป้องกันไม่ให้ซิมของคุณถูกใช้จากการใช้โดยผู้อื่นที่ไม่อนุญาตหากรหัส PIN ปิดคุณสามารถเปิดให้ใช้งานได้ด้วยตัวเอง เครื่องจะถามรหัส PIN ครั้งถัดไปที่โทรศัพท์เปิดอยู่. หากรหัส PIN เปิดคุณสามารถปิดเพื่อยกเลิกการป้องกันตน. คุณสามารถเปลี่ยนรหัส PIN โดยต่อไปนี้แสดงหน้าจอ: ใส่รหัส PIN ก่อนหน้าใส่รหัส PIN ใหม่และใส่อีกครั้ง.
- *หมายเหตุ: ซิมจะถูกล็อคถ้า inputs ของรหัส PIN ผิดสามครั้ง. แล้วคุณต้องการรหัส PUK เพื่อปลดล๊อคซิม. รหัส PIN และรหัส PUK จะจัดให้โดยโปรดติดต่อจัดหาเครือข่ายของคุณ. รหัส PIN เริ่มต้นคือ 1,234; โปรดเปลี่ยนเป็นรหัสผ่านส่วนบุคคลของคุณ.

2 , การล๊อคเบอร์โทร : หากเปิดใช้งานเพียงตัวเลขที่กำหนดในรายการหรือตัวเลขที่เริ่มต้นด้วยตัวเลขในรายการสามารถทำ. (สนับสนุนโดยซิม.)

○ โหมด: เปิดหรือปิดฟังก์ชัน (ต้องใส่รหัส PIN2.)

- รายการโทร แบบการล๊อคเบอร์โทร: ใส่หมายเลขโทรศัพท์จากรายการ.

*หมายเหตุ: เปิดหรือปิดฟังก์ชันการโทรคงต้องใส่รหัส PIN2 โปรดติดต่อเจ้าหน้าที่เครือข่ายของคุณ รหัส PIN2. ป้อนการล๊อคเบอร์โทร; หมายเลขของสายที่กำหนดจะปรากฏในไดเรกทอรี

3 , Barred Dial: การโทรที่ คุณสามารถจำกัดการโทรของตัวเอง

4 , เปลี่ยนรหัสผ่าน: เปลี่ยนรหัสผ่านของรหัส PIN, รหัส PIN2 และโทรศัพท์.

*หมายเหตุ: บางฟังก์ชันเป็นบริการเครือข่าย

- การตั้งค่าการรักษาความปลอดภัย SIM2

เดียวกันกับการตั้งค่าการรักษาความปลอดภัย SIM1.

- ล็อคโทรศัพท์:

ล็อคโทรศัพท์จะป้องกันโทรศัพท์ของคุณจากการใช้คนที่ไม่ได้รับอนุญาต เลือกโทรศัพท์ล็อคเพื่อเปิดใช้ การป้องกันการโทรศัพท์ เครื่องจะถามรหัสผ่านในครั้งถัดไปจะเปิด; กดอีกครั้งเพื่อยกเลิกการป้องกัน

- ใช้ ปุ่มทางขวา เพื่อยกเลิกการเข้าผิดเมื่อป้อนรหัสผ่านและกด OK เพื่อยืนยัน.

ตัวอย่างเช่นถ้ารหัสผ่านตั้งเป็น 1122 ป้อน: 1122.

*หมายเหตุ: รหัสผ่านเริ่มต้นของการลีดคโทรศัพท์เป็น 1122; โปรดเปลี่ยนเป็นรหัสผ่านส่วนบุคคลของคุณ หากคุณลืมรหัสผ่านของโทรศัพท์ของคุณคุณจะต้องติดต่อตัวแทนจำหน่ายหรือศูนย์บริการท้องถิ่นเพื่อปลดลีดคโทรศัพท์ของคุณ ลีดคปุ่มอัตโนมัติ ปุ่มจะลีดคตัวเองหลังจากที่โทรศัพท์จะไม่ได้ใช้เวลาที่กำหนดคุณกำหนด.

- เปิดลีดคปุ่มโดยการ: กดส่งคีย์เพื่อปลดลีดคปุ่ม
- การตั้งค่าโรงงาน Reset เพื่อเริ่มต้นการตั้งค่ารหัสผ่านของ 1122.
- เสียงประกอบ
- กำหนดเสียงประกอบของเครื่องเล่นเสียง: Equalizer , Reverb , 3D

3.5 มัลติมีเดีย

- การรับทีวี

งาน ทีวี ใช้การค้นหาด้วยตนเองหรือโดยอัตโนมัติเพื่อขอรับช่องให้ตรง

*หมายเหตุ: การทำงานต้องเลือกการตั้งค่าช่องและได้รับสัญญาณทีวีได้ดีขึ้นโดยการปรับเสาอากาศ

- ช่อง:เลือกช่องของฉัน . สามารถใช้หรือช่องโปรดบันทึกลงในรายการของช่อง. เพื่ออำนวยความสะดวกช่องทางออกอากาศที่เลือก.
 - ช่องทางของฉัน : รายการช่องทางของฉันสามารถใช้เพื่อรักษาช่องของตัวเอง
 - เลือกพื้นที่: พื้นที่อื่นให้ตั้งค่าสำหรับการเลือก
 - Auto ค้นหา: สามารถค้นหาช่องอัตโนมัติ. ช่องสัญญาณจะถูกบันทึกไว้ในรายการของช่อง. คุณเลือกได้จากช่อง.
 - รายการ ช่อง :ช่องที่ติดตามแต่ละพื้นที่
 - ลำโพงดัง: เปิดหรือปิดลำโพงดัง.
 - ตั้งค่าแสดงผล
- ความสว่าง : ปรับความสว่างของโทรทัศน์
 - แสดงความแรงของสัญญาณ : เปิดหรือปิดการแสดงความแรงของสัญญาณ.
 - แสดงสัญญาณอ่อนแอ : เปิดหรือปิดการแสดงสัญญาณอ่อนแอ.
 - กล้องถ่ายรูป ถ่ายรูปกล้อง

โทรทัศน์จะติดตั้งกล้อง. เข้าไปในกล้องและกด ok เพื่อเริ่มต้นการภาพถ่าย. ตัวเลือกมีดังนี้

- รูปภาพ: เข้าไปในอัลบั้ม.
- กล้อง Settings: ตั้งค่าพารามิเตอร์ที่เกี่ยวข้องของภาพการ

- การตั้งค่ารูปภาพ: กำหนดขนาดและคุณภาพของภาพถ่าย.
- White Balance: กำหนดสีของไฟ.
- โหมดฉาก: ตั้งโหมดของอัตโนมัติหรือถ่ายตอนกลางคืน
- การตั้งค่าผล: เลือกสไตล์แสดง.
 - เพิ่มกรอบ: เลือกเฟรมสำหรับภาพ
- Storage: บันทึกรูปภาพในโทรศัพท์หรือการ์ดหน่วยความจำ.
 - เริ่มต้น ตั้งให้ค่าเริ่มต้น
- โปรแกรมดูรูปภาพ

เก็บภาพมาจากกล้อง.

- ดู: ขยายภาพที่เลือก.
 - สไตล์ Browse: เปลี่ยนโหมดของภาพดู.
 - หน้า: ใช้ภาพที่เลือกเป็น, สกรีนเซฟเวอร์เปิด / ปิดภาพยนตร์และ
การเพิ่มสมุดโทรศัพท์.
- Rename: เปลี่ยนชื่อภาพที่เลือก.

- ลบ: ลบภาพที่เลือก.
- ลบไฟล์ทั้งหมด: ลบภาพทั้งหมดในอัลบั้ม.
- เรียงตาม: เรียงภาพของโฟลเดอร์ที่เลือกโดยใช้ชื่อพิมพ์วันที่หรือขนาด.
 - Storage: เปลี่ยนหรือเลือกเส้นทางที่เก็บค่าเริ่มต้นสำหรับรูปภาพ.
- บันทึกวิดีโอ

โทรศัพท์จะติดตั้งเครื่องอัดวิดีโอ เข้าไปในภาพยนตร์บันทึกและกด ok เพื่อเริ่มการบันทึกภาพยนตร์.

ตัวเลือกมีดังนี้ :

- เพื่อเล่น : เข้าไปในเครื่องเล่นภาพยนตร์และเล่นหนังบันทึก
- วิดีโอ Settings: ตั้งค่าพารามิเตอร์ที่เกี่ยวข้องของบันทึก
- Video Settings: กำหนดขนาดรูปแบบการบันทึกเวลาและผลที่มีคุณภาพเสียงของภาพยนตร์.
- การตั้งค่าผล: เลือกผลพิเศษสำหรับบันทึก.
- Storage: บันทึกภาพในโทรศัพท์หรือการ์ดหน่วยความจำ.
 - เริ่มต้น Restore: ตั้งให้ค่าเริ่มต้น

- เครื่องเล่นวีดีโอ

เรื่องเล่นที่จัดเก็บจากผู้ใช้. ตัวเลือกมีดังนี้

- เล่น: เล่นไฟล์ที่เลือก.
 - ข้างหน้า: การโอนไฟล์เลือกสมุดโทรศัพท์สกรีนเซฟเวอร์และเปิดหน้าออก /.
-
- Rename: เปลี่ยนชื่อไฟล์เลือก.
 - ลบ: ลบไฟล์ที่เลือก.
 - ลบไฟล์ทั้งหมด: ลบไฟล์ทั้งหมด.
 - เรียงตาม: จัดแฟ้มในแง่ของชื่อพิมพ์วันที่ขนาดหรือไม่มี).
-
- Storage: ตรวจสอบตำแหน่งของแฟ้ม (ในโทรศัพท์และการ์ดหน่วยความจำ).

เลือกเครื่องเล่นเสียง เข้าไปในเสียงเครื่องเล่น

เล่น: เล่นไฟล์ที่เลือก.

- รายละเอียด: ตรวจสอบรายละเอียดของเพลง

- เพิ่มเสียงเรียกเข้า: เพิ่มเพลงลงในห้องสมุดเสียงเรียกเข้าของโปรไฟล์.
- รายการรีเฟรช: คือการ update รายการเพลงให้เข้าเครื่อง
- การตั้งค่า: ตั้งเล่นไฟล์มัลติมีเดีย.
- รายการเพลงที่ตั้ง: ตั้งค่าเริ่มต้นเส้นทางการอ่าน.
- สร้างรายชื่อโดยอัตโนมัติ: ที่จะปรับปรุงรายการเพลงเวลาโทรศัพท์ทุกเปิดอยู่หรือไม่.
- ทำซ้ำ: ทำซ้ำเล่น.
- สุ่ม: เล่นแบบสุ่ม.
- เล่นประกอบ: การเล่นจะไม่หยุด จะหยุดเมนูเมื่อออก
- Sound Effects: ตั้งผลเสียงของเครื่องเล่นเสียง.
- แสดง Spectrum: เลือกสเปกตรัมสำหรับการเล่น
- BT ออกสแตอริโอ: เลือกให้เสียงออกสแตอริโอ Bluetooth
- หูฟังสเตอริโอ A2DP: เลือกหูฟังสเตอริโอ Bluetooth

ในขณะที่สแตนบายปุ่ม I และ O คีย์ปรับระดับเสียง

ในขณะที่โทรปุ่ม I และ O คีย์ปรับระดับเสียง

ในโหมดของเพลงปุ่ม I และ O คีย์ปรับระดับเสียง

การบันทึก

เลือกที่จะบันทึก. Touch คีย์ทางซ้ายปุ่มดำเนินการ:

- บันทึก: บันทึกเสียงใหม่
- เล่น: เล่นเสียงบันทึกที่เลือก
- ต่อท้าย:: เพิ่มบันทึกใหม่ในบันทึกเดิม. (สำหรับรูปแบบ AMR)
- Rename: เปลี่ยนชื่อบันทึก
- ลบ: ลบบันทึกปัจจุบัน
- ลบไฟล์: ลบบันทึกทั้งหมด
- ตั้ง: กำหนดรูปแบบบันทึกของ
- ส่งต่อ: ส่งบันทึกไปรโฟลหรือ ส่ง โดยข้อความมัลติมีเดีย.

วิทยุ FM

โทรศัพท์สนับสนุนการฟังวิทยุ FM. เลือกปุ่มทางลัด FM เพื่อไปดำเนินการ กดเลือกคีย์ที่จะดำเนินการต่อไปนี้

- รายการ Channel "แก้ไขชื่อช่องทางและแสดงในรายการ
- คู่มือ Input: ความถี่ช่องโดยตรงเช่น 103.5
- ค้นหาอัตโนมัติตั้ง: automaticly ค้นหาช่องทาง FM และปรับปรุงรายการ.
- การตั้งค่า: เล่นออกถ้าโพงหลัง
- บันทึก: บันทึกเสียงใหม่
- ต่อท้าย: เพิ่มบันทึกใหม่เดิมหนึ่ง.

- รายชื่อไฟล์: โฟล์บันทึก.

3.6 จัดการไฟล์

- หน้าที:
- เปิด: แสดงเนื้อหาของโฟลเดอร์.
- สร้าง: สร้างโฟลเดอร์ใหม่ภายใต้โฟลเดอร์ปัจจุบัน.
- รูปแบบ: รูปแบบโฟลเดอร์.
- Rename: เปลี่ยนชื่อแฟ้มหรือโฟลเดอร์.
- ลบ: ลบแฟ้มหรือโฟลเดอร์.
- จัดเรียง: จัดเรียงไฟล์หรือโฟลเดอร์.
- รายละเอียด: ตรวจสอบรายละเอียดของแฟ้มหรือโฟลเดอร์.
- Copy: คัดลอกแฟ้มหรือโฟลเดอร์ในตำแหน่งใด.
- ย้าย: ย้ายแฟ้มหรือโฟลเดอร์ในตำแหน่งใด.
- ลบ: ลบแฟ้มทั้งหมดหรือโฟลเดอร์ของโฟลเดอร์ปัจจุบัน.
- โฟลเดอร์

เสียง- เส้นทางการจัดเก็บค่าเริ่มต้นของเสียง.

ภาพ -: เส้นทางการจัดเก็บค่าเริ่มต้นของภาพ.

เพลงของฉัน : โพลเดอร์สำหรับไฟล์เสียงที่อัปโหลดและเส้นทางการอ่านค่าเริ่มต้นของการเล่นเสียง.

รูปภาพ: เส้นทางการจัดเก็บค่าเริ่มต้นของรูปภาพ.

วิดีโอ: เส้นทางการจัดเก็บค่าเริ่มต้นของวิดีโอ .

3.7 สนุกและเกม

- จาวา

THE J2ME โปรแกรม java

- เกมส์
- Majung :

- เกมใหม่: เริ่มเกมใหม่.
- โหมด Game: เลือกระดับเกมส์.
- เกรดดีที่สุด: บันทึกบันทึกการเล่นเครื่องเล่นของ.
- ช่วย: ไปดูกฎเกมส์.
- ชูชิ Magic operaion เมนู (ตามที่ระบุเช่นเดียวกับด้านบน)
- ตั้งค่าเกม
- BGM: เปิด / ปิดเพลงพื้นหลัง
- ผล Sound: เปิด / ปิดผลเสียง
- สั่น Games: เปิด / ปิดการสั่นสะเทือนเกมส์.

3.8 โพรไฟล์ผู้ใช้

โดยทั่วไป ทัวไปโดย

เปิด: เปิดใช้งานรูปแบบทัวไป

- กำหนด: ป้อนในการตั้งค่าส่วนบุคคลของโปรไฟล์ทัวไป. หน้าที่ดังนี้
- เสียงเรียกเข้า: เปลี่ยนเสียงเรียกเข้าสำหรับการโทรเข้ามานาฬิกาปลุกโทรศัพท์ / ปิดโทรศัพท์ที่เลือกข้อความ
- ระดับเสียงเรียกเข้า: ปรับระดับเสียงเรียกเข้า
- ชนิด เสียงเรียกเข้า: เสียงเรียกเข้า, การสั่น, การสั่นสะเทือนและเสียงเรียกเข้า, เสียงเรียกเข้าหลังจากการสั่นสะเทือน.

- เข้า Call Alert: เสียงเรียกเข้าแบบค่อยๆดังหรือ ascending.
- ข้อความ Alert Tone: ตั้งเสียงเตือนสำหรับการเตือน, ข้อผิดพลาดการเชื่อมต่อเครือข่ายหรือการเชื่อมต่อโทร.
- ตอบ Mode: ตั้งได้สำคัญในการรับสายเรียกเข

การประชุม

เช่นเดียวกับรูปแบบทั่วไป.

- กลางแจ้ง

เช่นเดียวกับรูปแบบทั่วไป.

- ในร่ม

เช่นเดียวกับรูปแบบทั่วไป.

- หูฟัง

โดยอัตโนมัติเมื่อเปิดใช้งานรูปแบบหูฟังมีการเชื่อมระบบที่เหลือเป็นเหมือนกับรูปแบบทั่วไป.

บลูทูธ

เช่นเดียวกับรูปแบบทั่วไป

3.9 จัดงาน ORGANIZER

Calendar

เข้าไปในเมนูย่อยของ Calendar

- Calendar: สร้างกิจกรรมใหม่และเพิ่มนาฬิกาปลุกไปด้วย ผู้ใช้สามารถกำหนดรายวัน กำหนดสัปดาห์และรายเดือน.
- เมื่อกรณีที่จะเตือนเพียงครั้งเดียว.
- วัน: กรณีที่จะเตือนในเวลาที่กำหนดไว้ทุกวัน.
- ผู้ใช้กำหนด: จะเตือนเมื่อสัปดาห์ที่กำหนดโดยผู้ใช้.
- สัปดาห์: กรณีที่จะเตือนในเวลาที่กำหนดไว้ทุกสัปดาห์.
- รายเดือน: กรณีที่จะเตือนในเวลาที่กำหนดไว้ทุกเดือน.
- ข้ามไปยังวันที่ระบุ: กระโดดจากวันที่ปัจจุบันในวันที่ระบุ.
- จันทรคติ Calendar: เปิดหรือปิดจันทรคติ.

* หมายเหตุ: เนื่องจากขีดจำกัดของหน่วยความจำที่เก็บรายการไม่ควรเกิน 70; รายการอื่นอาจหายไป

- การทำรายการ

- เพิ่ม

- วันที่: วันที่ของรายการบันทึก.
- Time: เวลาของรายการบันทึก.
- หมายเหตุ: ข้อความที่ปรากฏบนหน้าจอเดือนเมื่อ.
- ปลุกนาฬิกา: เปิดหรือปิดนาฬิกาปลุก.
- Mode:

เมื่อ: เดือนเพียงครั้งเดียว.

วัน: ตักเตือนในเวลาที่กำหนดไว้ทุกวัน.

ผู้ใช้กำหนด: ตั้งเวลาเตือนของนาฬิกาปลุกในสัปดาห์.

สัปดาห์: เดือนเพียงครั้งเดียวในสัปดาห์.

รายเดือน: เดือนเพียงครั้งเดียวในเดือน.

- ดู: รายการตรวจสอบที่เก็บไว้.
- เพิ่ม: เพิ่มรายการใหม่
- แก้ไข: แก้ไขรายการที่เก็บไว้.
- ลบ: ลบรายการที่เลือก.

- ลบทั้งหมด: ลบรายการทั้งหมด.
- โอนเงิน: โอนรายการที่เลือกไปยังโทรศัพท์อื่นโดยการส่งข้อความหรือเก็บไว้ในคลังของโทรศัพท์.
- ปลุก ปลุก
- /ปิด: เปิดหรือปิดนาฬิกาปลุก.
- Time: ตั้งเวลาปลุก

Mode:

- เมื่อ: เตือนเพียงครั้งเดียว.
- วัน: ตักเตือนในเวลาที่กำหนดไว้ทุกวัน.
- ผู้ใช้กำหนด: ตั้งเวลาเตือนของนาฬิกาปลุกในสัปดาห์.
- ตั้งค่า เสียงเรียกเข้า :

เลือกเพลงหรือบันทึก FM บันทึกเป็นเสียงเรียกเข้า

- เวลาเลื่อนการเตือน (นาที) :

เลือกที่จะสับกลับทุกไม่กี่นาที. มี 11 ตัวเช่นทุก 1 นาทีทุก 10 นาที

- วิธี เสียงเรียกเข้า: เสียงเรียกเข้าตัวเป็น การสั่น, การสั่นสะเทือนและเสียงเรียกเข้า

นาฬิกาโลก

ทิศทางใช้คีย์อ่านโซนเวลาของแต่ละเมืองและวันที่และเวลาในแต่ละเมือง.

3.10 การบริการ

- WAP
- ฟังก์ชันเมนู:
- หน้าแรก: เข้าสู่ระบบหน้าแรก. หน้าแรกเป็นเว็บไซต์ WAP ที่คุณกำหนดในการตั้งค่าการเชื่อมต่อ. หากคุณยังไม่ได้กำหนดว่าจะใช้ชุดเดียวโดยผู้ผลิต.
- บัญคอร์ด: แสดงบัญชีคอร์ดที่มี. เลือกเพื่อเชื่อมต่อกับเว็บไซต์.
- ประวัติ: เก็บเว็บไซต์ที่คุณเล่น internet และบันทึก.
- ใส่ Address: ใส่ที่เว็บไซต์ WAP อินเทอร์เน็ตหรือเว็บไซต์อื่นๆ.
- การตั้งค่า: ให้ตั้งค่าของเว็บไซต์ที่เรียก.
- แก้ไขการตั้งค่าโปรไฟล์: เลือกข้อมูลการตั้งค่าใน 10 ตัวเลือกให้.
- ท้อง Properties: การตั้งค่าพารามิเตอร์ของการเรียกดูเว็บไซต์รวมถึงเวลาสแตนด์บายและแสดงภาพ.
- บริการข้อความ: ข้อความบริการเปิดหรือปิด.
- หน่วยความจำแฟลช: ลบหน่วยความจำแฟลช.
 - ล้างข้อมูลส่วนบุคคล: ล้างข้อมูลส่วนบุคคลของ.
 - ประวัติการลบ: ลบประวัติการ.

- ไบรรับรอง: ตรวจสอบไบรรับรอง.
- ทำงานออนไลน์
- Jump to: ข้ามไปยังที่อยู่โดยตรง.
- Right Soft Key (Back) กลับไปหน้าก่อนหน้านี้
- หน้าแรก: กลับไปที่หน้าแรก
- Refresh: รีเฟรชหน้าเว็บ
- บุ๊คมาร์ค: แสดงบุ๊คมาร์คที่มี. เลือกเพื่อเชื่อมต่อกับเว็บไซต์แก้ไขที่อยู่หรือชื่อของบุหรือลบบุ๊คมาร์ค.
- History: ตรวจสอบเว็บไซต์ที่คุณ surfed ในรายการ
- ป้อนที่อยู่: ใส่ URL โดยตรงไปยังเว็บไซต์
- ตั้งเป็นหน้าแรก: ตั้งหน้าปัจจุบันเป็นหน้าแรก
- บันทึกภาพ: บันทึกภาพของหน้าปัจจุบัน.
- บริการ Inbox: ตรวจสอบกล่องจดหมายของบริการข้อความ.
- การตั้งค่า: เข้าไปในเมนูการตั้งค่า.
- ออก: ออกจาก explorer WAP และกลับไปเมนูหลัก.

*หมายเหตุ: บริการ GPRS เป็นการสนับสนุนของเครือข่ายและมีเฉพาะหลังจากให้บริการนี้ออกทำงาน

- ข้อมูลบัญชี

- ข้อมูล GSM :
- ชื่อ: ชื่อของบัญชี. คุณสามารถแก้ไข.
- จำนวน: จำนวนบัญชี.
- ผู้ใช้บัญชี: เลขที่บัญชีของ server (ไม่เกตเวย์ WAP).
- Password: รหัสผ่านของโทร server (ไม่เกตเวย์ WAP).
- Line Type: สายอนาล็อกหรือดิจิตอล line.
- Speed: เลือกความเร็วในการโอนเงินที่เหมาะสม.
- เครือข่ายโดเมน: ที่อยู่ IP .

GPRS :

- ชื่อ: ชื่อของบัญชี. คุณสามารถแก้ไข.
- GPRS เชื่อมโหนด: ใส่ APN.
- ผู้ใช้บัญชี: เลขที่บัญชีของโทร server (ไม่เกตเวย์ WAP).
- Password: รหัสผ่านของโทร server (ไม่เกตเวย์ WAP).
- รับรอง: เลือกวิธีการเข้ารหัสของใบรับรอง.

Wireless LAN:

- เปิด WLAN: เปิดและปิดการใช้งาน WLAN

- สถานะ WLAN: แสดงสถานะ WLAN.

เช่นที่อยู่อุปกรณ์, SSID, BSSID ช่องความแรงสัญญาณความเร็วลิงก์ที่อยู่เป็นต้น.

- เข้าถึงการตั้งค่าจุด

1.connect: เชื่อมต่อและปลด AP

2.Edit: แก้ไขการตั้งค่า AP.

เช่น SSID, Network, TCP / IP, โหมดความปลอดภัยโหมด Encryption.

จุดเชื่อมต่อ

3.New: การตั้งค่าจุดเชื่อมต่อ

4.Delete : ลบจุด.

5.change สำคัญ: การเปลี่ยนแปลงลำดับความสำคัญ.

- ค้นหาเครือข่าย: ค้นหาเครือข่ายที่มี.

1.connect: เชื่อมต่อและปลด AP

จุดเชื่อมต่อ 2.Define: กำหนดค่า AP.

3.Details: แสดงรายละเอียด AP

4.Refresh: รีเฟรชรายการเครือข่ายที่มี.

STK

STK เป็นบริการเพิ่มเติมโดยการจัดหาเครือข่าย. เมนูการทำงานต่างจากแต่ละซิม.

3.11 เพิ่มเติม

เครื่องคิดเลข

- กดปุ่ม 0-9 สำหรับป้อนข้อมูลตัวเลขและ # สำคัญสำหรับที่ของจุดทศนิยม.
- กดปุ่มขึ้นลงซ้ายและขวาสำหรับใส่ของสัญลักษณ์ทางคณิตศาสตร์ของ + , -- , X , ÷ .

- กด ปุ่มทางขวา ลบรายการสุดท้าย. กด ปุ่มทางขวา จะออก "เครื่องหมายคิดเลข" และ กด ปุ่มทางซ้าย "การรับ"

* หมายเหตุ: ความแม่นยำของเครื่องหมายคิดเลขที่ถูกจำกัด. อาจมีการจับข้อผิดพลาดโดยเฉพาะอย่างยิ่งเมื่อตัวเลขไม่สามารถแบ่ง

- แปลงหน่วย
- น้ำหนัก: รวมการแปลงระหว่างกิโลกรัม < -- > ปอนด์และกิโลกรัม < -- > ออนซ์. ใส่จำนวนลงในช่องที่เกี่ยวข้องกับ กด ปุ่มทางซ้ายเพื่อยืนยัน. ผลจะปรากฏขึ้นในสาขาอื่นๆ.
- ความยาว: รวมการแปลงระหว่างกิโลเมตร < -- > ไมล์, เมตร < -- > หลา, เมตร < -- > เท้าและเซนติเมตร < -- นิ้ว>. ใส่จำนวนลงในช่องที่เกี่ยวข้องกับ กด ปุ่มทางซ้ายเพื่อยืนยัน. ผลจะปรากฏขึ้นในสาขาอื่นๆ.
- แปลงหน่วยเงินตรา เงินตราแปลงหน่วย

ดำเนินการแปลงในสกุลเงินใดๆ. คุณต้องป้อนอัตราแลกเปลี่ยนเป็นครั้งแรกแล้วจำนวนสกุลเงินในประเทศหรือของสกุลเงินต่างประเทศและกด Soft Key ซ้ายเพื่อยืนยัน. ผลจะปรากฏขึ้นในสาขาอื่นๆ

สุขภาพ

- ดัชนีของคุณภาพทางกายภาพ

บ๊องและเลือกชายหรือหญิง; ใส่ความสูงและน้ำหนักและกด OK. ผลจะแสดงในแผนภาพแสดงช่วงของดัชนีคุณภาพทางกายภาพของคุณ.

นาฬิกาจับเวลา

- คำนวณเวลาที่จะได้.

- E-Book reader
- Ebook เปิด: เปิดไฟล์ ebook.
- ชั้นวางหนังสือ Cleanup : Updata รายการ ebook.
- การตั้งค่า ค่าการตั้ง

- แบบอักษร: เลือกลักษณะแบบอักษรสำหรับ Normal, ตัวเอียงและตัวหนา

- เลื่อนโดย: เลือกเลื่อนตามหน้าและบรรทัด

เลื่อนอัตโนมัติ -: เปิดและปิดเลื่อนอัตโนมัติ

- ความเร็วในการเลื่อนไป: เลือกความเร็วในการเลื่อนอัตโนมัติ

- หน้าจอเต็ม: เปิด และเลือกโหมดเต็มหน้าจอ

- รูปแบบการเข้ารหัส: เลือกการเข้ารหัส ebook

หน่วยความจำ -: เลือกหน่วยความจำบัตรหน่วยความจำหรือโทรศัพท์.

- ข้อมูล: แสดงข้อมูล ebook.
- ลบ: ลบไฟล์ ebook.
- ลบ: ลบทั้งหมด ebook ในรายการ.
- การตั้งค่าเริ่มต้น: Restore การตั้งค่าเริ่มต้น.
- ช่วย: ข้อมูลช่วยเหลือ.

Bluetooth

โทรศัพท์จะติดตั้งเทคโนโลยีบลูทูธและรองรับตามโหมดข้อความและโหมดอื่นๆ. Bluetooth ตั้งค่าเมนูดังนี้

- เปิด: เปิดหรือปิด Bluetooth.
- ค้นหาอุปกรณ์ ที่ว่าง: ค้นหาชื่อ Bluetooth ปัจจุบันอุปกรณ์ที่ว่าง
- อุปกรณ์: รายชื่อของอุปกรณ์ของฉันมีการเชื่อมต่อ.
- อุปกรณ์ในการเชื่อมต่อ: อุปกรณ์การเชื่อมต่อ.
- การตั้งค่า: รวมการตั้งค่าต่างๆเช่นการค้นหาเพิ่มการถ่ายโอนการตั้งค่า
- My Bluetooth: ตรวจสอบสถานะของ Bluetooth.

สร้างการเชื่อมต่อ Bluetooth

เปิดใช้งาน Bluetooth, Device ที่รีเลือก "ค้นหา Hands" หรือลง "Device ของฉัน" -- "Option"
-- ค้นหา "สำหรับอุปกรณ์ใหม่" เพื่อค้นหาอุปกรณ์บลูทูธในช่วงที่มีประสิทธิภาพ บ่อนรหัสผ่าน
ตกลงสร้างตรงระหว่างอุปกรณ์ก่อนที่จจะโอนข้อมูล.

หลังจากที่เชื่อมต่อกับ Bluetooth, หน้าต่อไปนี้จะใช้ได้กับอุปกรณ์เชื่อมต่อ

- ติดต่อ: อุปกรณ์ได้รับข้อมูลจากอุปกรณ์เชื่อมต่อ
- ชื่อ Device: เปลี่ยนชื่ออุปกรณ์ของด้านอื่นๆ.
- ลบ: ลบชื่อของอุปกรณ์ที่เลือก.
- ลบ: ลบบันทึกทั้งหมดในรายการอุปกรณ์.
- บริการบันทึก: ตรวจสอบบริการที่มี.
- ค้นหาอุปกรณ์ใหม่: ค้นหาอุปกรณ์ใหม่ภายในช่วงที่มีประสิทธิภาพ.

*หมายเหตุ:

1ใช้เทคโนโลยี Bluetooth, โทรศัพท์สามารถในการเชื่อมต่อกับอุปกรณ์รองรับบลูทูธภายในระยะ
10 เมตร แต่การเชื่อมต่ออาจมีผลกระทบจากอุปสรรคเช่นผนังหรืออุปกรณ์อิเล็กทรอนิกส์อื่นๆ.

2.ใช้ Bluetooth อาจเร่งการใช้พลังงานแบตเตอรี่และอายุแบตเตอรี่ ก็แนะนำให้เปิด
Bluetooth ปิดเมื่อไม่จำเป็นต้อง

3. ให้การเชื่อมต่อที่ราบรื่นระหว่างโทรศัพท์และเทคโนโลยีไร้สายอื่นๆ อุปกรณ์สนับสนุนโปรดใช้อำนาจเสริมจากผู้ผลิตอุปกรณ์ โปรดตรวจสอบว่ามีการผลิตในกรณีที่คุณพกพาเข้ากันได้กับโทรศัพท์. .

3.12 เมนูลัด

โทรศัพท์ให้ 11 ทางลัด. เปิดเมนูและเลือกทางลัดเพื่อรับหน้าที่เป็นทางลัด

บทที่ 4 การแก้ปัญหา

การตั้งค่าการทำงานบางอย่างล้มเหลว	หน้าที่ดังกล่าวอาจจะไม่ได้สนับสนุนจากเครือข่ายหรือคุณใช้ไม่ได้กับเครือข่าย
PIN ล็อก	ป้อนรหัสผ่านและรหัส PUK ซิม ต้องติดต่อเครือข่าย.

PIN2 ที่ถูกล็อค	ป้อนรหัสผ่านและรหัส PUK ซิม ต้องติดต่อเครือข่าย.
การคิดค่าโทรผิดไม่ถูกต้อง	โปรดติดต่อเครือข่ายของคุณ.
ซิมการ์ดผิดพลาด	<ol style="list-style-type: none"> 1. ซิมอาจจะสกปรกสะอาด. 2. ติดตั้งซิมผิด 3. ซิมเสียหายหนึ่งเปลี่ยน.

ขอสงวนที่เหมาะสมสำหรับการตีความด้วยตนเองนี้.

ขอสงวนผลิตรที่เหมาะสมสำหรับการเปลี่ยนแปลงในมาตรฐานทางเทคนิคโดยไม่ต้องแจ้งให้ทราบล่วงหน้า

ขอสงวนผลิตรที่เหมาะสมสำหรับการเปลี่ยนแปลงในนี้ด้วยตนเองโดยไม่ต้องแจ้งเพิ่มเติม.

6 รายละเอียดการรับรอง (SAR)

เครื่องโทรคมนาคมและอุปกรณ์นี้ มีความสอดคล้องตามคำแนะนำระหว่างประเทศของการสื่อสารทางคลื่นวิทยุ เครื่องโทรศัพท์ของคุณจะเป็นตัวรับและส่งสัญญาณวิทยุ ซึ่งได้รับการออกแบบและได้รับการผลิตไม่ให้เกิดความถี่สัญญาณคลื่นวิทยุ ที่แนะนำโดยข้อกำหนดระหว่างประเทศ (ICNIRP)

มาตรฐานของการเปิดรับคลื่นโทรศัพท์เคลื่อนที่นี้ใช้หน่วยวัดของ SAR (Specific Absorption Rate) ข้อกำหนดที่กำหนดไว้ในคำแนะนำระหว่างประเทศคือ 2.0 วัตต์/กิโลกรัม (W/kg)*

ค่า SAR สำหรับโทรศัพท์เมื่อทำการทดสอบโดยใช้งานใกล้เคียงกับหูจะเท่ากับ 0.43 วัตต์/กิโลกรัม ค่า SAR แตกต่างกันไปโดยขึ้นอยู่กับข้อกำหนดที่รายงานของแต่ละประเทศและข้อกำหนดในการทดสอบรวมทั้งระบบเครือข่ายด้วย การใช้อุปกรณ์เสริมอาจมีผลทำให้ค่า SAR แตกต่างไปด้วยเช่นกัน

หมายเหตุ “เครื่องโทรคมนาคมและอุปกรณ์นี้ มีความสอดคล้องตามข้อกำหนดของ กทท.”

CHAPTER 1 Safety Information

1.1 General Precautions

- Please turn off your phone in an airplane, hospital or areas where the phone may disturb the operation of sensitive or medical equipment. Please use your phone in accordance with the rules of the areas.
- To prevent the disturbance of the radio wave from causing malfunction or other problems, do not use your phone around weak signal or high accuracy electronic equipment, especially otophone, pacemaker or other medical equipment, fire detector, auto-controlled door and devices.
- Do not knock violently, shake or toss the phone; otherwise the phone may break down or cause fire.
 - Do not put the battery, phone, or the charger into a microwave oven or high tension apparatus; otherwise the phone may break down.
 - Do not use the phone in areas with a potentially explosive atmosphere; otherwise the phone may break down or cause fire.
 - Do not put the phone in areas with high temperature, high humidity or with air that contains dust; otherwise the phone may break down.
 - Keep the phone out of a child's reach; otherwise the child may take it as a toy and suffers injury.
 - Do not put the phone on an uneven or unsteady table; otherwise the phone may fall off and break.
 - Do not dismantle or refit the phone; otherwise the phone may break down or cause electric leakage or other problems.
 - Do not use needle, stylus or pointed objects to press the keys; otherwise the phone may break down and malfunction.
 - Prevent the phone from nearing magnetic objects such as magnetic cards, credit cards, floppy disks. The radio wave of the phone may erase the information stored on them.

- Do not expose the phone to humidity, water or other liquid; otherwise the phone may break down.
- To prevent traffic accident, do not use the phone when driving.
- Always use the battery and battery charger authorized by the manufacturer. Such products of other brands may cause leakage, excessive heat, burst and fire.
- Only professional personnel are allowed to assemble and repair the phone. It may be of great danger and against warranty to assemble and repair the phone without permission.

1.2 Battery Precautions

- ◆ Do not throw the battery in fire; otherwise fire and burst may occur.
- ◆ Do not use force when removing the battery; otherwise leakage, excessive heat, burst and fire may occur.
- ◆ Do not short-circuit or put the battery together with metal objects like wire, needle and necklace; otherwise leakage, excessive heat, burst and fire may occur.
- ◆ Do not dismantle or refit the battery or weld the contact points otherwise leakage, excessive heat, burst and fire may occur.
- ◆ The liquid leaked from the battery may cause blind if entering into the human eyes. In this case, please wash the eyes with clean water immediately (do not rub the eyes) and go to hospital as soon as possible.
- ◆ Do not use and put the phone near areas of high temperature such as fire or heaters; otherwise leakage, excessive heat, burst and fire may occur.
- ◆ If the battery suffers heating up, discoloration or distortion during use, charging or storage, stop using it and change a new one.
- ◆ If the liquid leaked from the battery contacts skin or clothes, it may cause burn. Wash the skin or clothes with water or go to the hospital when necessary.
- ◆ If the battery leaks liquid or gives off bizarre odor, take it away from the open fire; otherwise leakage, excessive heat, burst and fire may occur.
- ◆ Prevent the battery from humidity otherwise excessive heat, fuming and erosion may occur.
- ◆ Do not use or place the battery under direct sunshine or near areas of high temperature such as automobiles; otherwise it may cause leakage and excessive heat as well as affect the performance of the battery and reduce its life span.
- ◆ Do not charge the batter over 24 hours on end.
- ◆ The battery life is limited and will be reduced after long and frequent charging. If it doesn't work after several charging, it indicates the end of its life. You need to replace it with new battery of specified model.
- ◆ Do not dispose of the battery with domestic garbage; instead you should

dispose of it in line with the regulations.

1.3Charger Precautions

- ◆ Use a 220V AC power; otherwise it may cause leakage, excessive heat and damage to the phone and charger.
- ◆ Do not short-circuit the charger; otherwise it may cause electric shock, fuming and damage to the charger.
- ◆ Do not use the charger when the power cord is broken; otherwise it may cause fire and electric shock.
- ◆ Do not put a container with water near the charger; otherwise water may spill out and enter into the phone to cause excessive heat, electric leakage and other problems.
- ◆ If contacted with water or other liquid, the charger must be removed from the power socket immediately to prevent excessive heat, fire, electric shock and other problems to the charger.
- ◆ Do not dismantle or refit the charger; otherwise injury to the human body, electric leakage and fire may occur.
- ◆ Do not use the charger in places of high humidity such as bathroom; otherwise electric leakage, fire and other problems to the charger.
- ◆ Do not touch the charger, power cord or power socket with a wet hand; otherwise electric shock may occur.
- ◆ Do not put heavy objects upon the power cord or refit it. Otherwise electric shock or fire may occur.
- ◆ Disconnect the charger with electric power during cleaning and maintenance.
- ◆ Hold the body of the charger other than the cord when disconnecting the charger with electric power; otherwise electric shock or fire may occur.
- ◆ If the contents of this manual are not consistent with your phone, the phone shall prevail.

CHAPTER 2 Phone Introduction

2.1 SIM Card

Before you use your phone, you must insert your SIM card. It's your key to enter into the GSM network. All the information related to the connection to the network and logs of calls is recorded in the metal area of the SIM card. Also recorded on the SIM card are names and calls in the phonebook as well as text messages. You can also take the SIM card out and put it into another GSM mobile phone. (The new phone will read the SIM card automatically)

To prevent the loss and damage of information stored on the SIM card, the metal area of the SIM card should not be touched and the card should be kept away from electrical and magnetic area. Once the SIM card is damaged, you are unable to enter into the GSM network.

TF (T--Flash) Card is the portable memory card with large capacity for storing music and video files, which considerably expands the storage room of the phone.

*Note: The phone must be turned off before you remove the SIM/ TF card. It's prohibited to insert or remove the SIM/ TF card when the phone is in connection with an external power supply; otherwise the SIM/ TF card may be damaged.

- ◆ Before installing the SIM card, turn the phone off and remove the battery as well as other external power.
- ◆ Insert the SIM card into the SIM slot and slide the SIM slot strip back.
- ◆ When the SIM card needs to be taken out, turn the phone off, open the back cover, remove the battery; then open the SIM slot strip and take the SIM card out of the slot.
- ◆ Before installing the TF card, turn the phone off and remove the battery as well as other external power.
- ◆ Insert the TF card into the TF slot.
- ◆ When the TF card needs to be taken out, turn the phone off and take the TF card out of the slot.

2.2 Battery

50% of the battery power is charged initially and can be used after unpacking.

The new battery needs to be charged for at least 14 hours. After the power is used up (with no power to turn the phone on) for the first time, charge the battery fully. For the second time, charge the battery fully again after the power is used up. And to do it the same way for three times to maximize its performance.

◆ Installing and Removing the Battery

Remove the battery in the following way:

1. Remove the battery cover by sliding it.
2. Uplift the battery from the backside and take it out.

Install the battery in the following way:

1. Lock the battery into the battery slot.
2. Push the back cover upward until it is locked firmly.

◆ Charging the Battery

Plug the charger into a power socket. The power is on when the power indicator light is lit

*Note: Don't take up the battery when the battery is charging.

Insert the connector of the charger into the port on the right side of the phone.

The battery symbol appeared at the top right corner indicates the state of charging. If the phone is turn off during charging, a charging indication picture will be shown instead signifying that charging is in progress. If the phone is in

low battery and being used overly, it may take a while for the charging icon to appear on the screen after charging is started.

When the charging bars are full and steady, it means charging is complete. If the phone is turn off during charging, a charging indication picture will be shown instead signifying that charging is complete. The process usually takes 3~4 hours. It is normal that the battery, phone and charger may generate some heat during charging.

When charging is complete, disconnect the charger from the phone and electric power.

*Note:

- The battery must be charged with the charger supplied by the manufacturer in a ventilated place with a temperature between $\square 5\square$ and $\square 40\square$. The use of unapproved charger may cause danger and will invalidate the warranty.
- Charge the battery when the phone is turned off automatically or displays the warning of low battery. If the battery has not used up, the charging time will be shortened.
- The standby time and talk time provided by the manufacturer is calculated in the ideal environment. The actual time may vary with the network condition, working condition and running mode.
- Make sure that the battery is well installed and can not be removed during charging.
- When charging is complete, disconnect the charger from the phone and

electric power.

- If the charger has not been disconnected from the phone and electric power, charging will start again after a certain amount of battery power is used in a period of 5~8 hours. This is not advised due to the fact that doing so may have some adverse impact on the life of the battery.

2.4 Data Line

◆ Connect the data line when the phone is turned off. The charging icon is displayed on the screen, which indicates that the phone is off and being charged.

◆ Connect the data line when the phone is turned on. Menus are displayed on the screen.

- Storage Unit: in the storage mode, contents of the phone can be accessed by the computer.
- Web Camera: in the camera mode, the phone can work as a camera.
- Charging: use the charging function only. The phone returns to standby, and the other functions are still available.

2.5 Power on/off

◆ Press and hold the Power Key to turn the phone on or off.

◆ If the phone is turned on without a SIM card, the message of "inserting the SIM card" will be shown. The SIM card will be checked out after being inserted. Then the following information will be shown on the screen: Enter PIN1 (if you

have set a password for the SIM card), Enter password of the mobile phone (if you have set a password for unlocking the phone).

◆ After the SIM card is decoded successfully, your phone will search for an available network (displayed on the screen). Once the connection is made, the icon of the network supplier will appear in the center of the screen. Now the phone is in standby and ready to use.

*Note: if “Emergency number” appears, it means you are out of the service area of the network. However, you can still make emergency calls according to the signal strength of your phone.

CHAPTER 3 Menu Details

3.1 Phonebook

➤ Quick Search: enter into the browse screen of the phonebook. You can enter corresponding information in the searching column below to sort the entries out. Modes of searching include: 1. English (lower case); 3. Number. Press the IME Key to switch among input methods.

- SIM1 IP Dial: activate the IP dial-up of numbers in the phonebook by SIM1
- SIM2 IP Dial: activate the IP dial-up of numbers in the phonebook by SIM2
- Send SMS: send message to the number
- View: check the details of entry
- Edit: edit the entry
- Delete: delete the entry

- Duplicate: backup the entry
 - Move: move the entry
 - Copy: copy the entry
 - Send vCard
 1. Send by SMS: send the entry via text message
 2. Send by MMS: send the entry via multimedia message
 3. Send by Bluetooth: send the entry via Bluetooth.
 4. Save to file: save the entry as electronic card.
 - Search contact: search the phonebook for entry by name.
 - Add new contact: add a new entry into the phonebook. You can store the entry into the SIM1 card , SIM2 card or the phone
- *Note: They are different from each other in terms of storage format
- Copy All: copy all the entries from the phone to the card1, card2 ; copy all the entries form the card to the phone, or copy all the entries form the card1 to card 2; or vice versa.
 - Delete: select the items to delete the call record. Select to delete all the call record from SIM card1 . Select to delete all the call record from SIM card12.Select to delete all the call record from the phonebook. Select to delete one by one of the call record.
 - Calls Groups: the phone is programmed with 5 calls groups. You can make individual setting for each group, such as rename, ring type, incoming call picture, incoming call film and each group member's personal setting.
 - Extra Number: Other numbers such as the caller ID, service number and

urgency number stored on the SIM card. You can check and edit other numbers stored on the SIM card.

* Note: service number need the support of SIM card.

➤ Settings: set the phonebook in four categories: Memory Check, Storage Location, Card Setting and My Card.

- Memory Check: check the memory of the SIM card and the phone.
- Storage Location: choose the preferred storage location, the phone or the SIM card.
- Card Setting: set the content of the entries in the phonebook.
- My Card: edit and save the detailed information of the user.

➤ Caller picture: choose a picture for an incoming call.

➤ Caller Ring tone: choose a ring for an incoming call

➤ Caller video: films supplied with the phone or captured by the users can be designated as the for the incoming call film. When a call is coming, the film designated will be played.

3.2Messages

◆ Text Message

➤ Inbox Can select the SIM1 Inbox or the SIM2 Inbox. Check the received messages. When the Inbox message list appears, press Ok to read the message. You can choose the following options!

- Reply: reply to the sender of the message.

- Delete: delete the message.
- Edit: edit the message.
- Forward: forward the message.
- Copy to SIM Card (Phone): copy the message from the phone to the SIM card, or vice versa.
- Move to SIM Card (Phone): move the message from the phone to the SIM card, or vice versa.
- Chat: enter into the chat room.
- Delete All: delete all the message in the inbox
- Copy All: copy all the message from SIM card to the phone or from the phone to SIM card.
- Move All: move all the messages from SIM card to the phone or from the phone to SIM card.
- Use Number: dial or store in the phonebook the number extracted from the message.
- Use Link: Extract and store the web link contained in the message.
- Outbox: Can select the SIM1 outbox or the SIM2 outbox check the un-sent messages. When checking the Outbox message list, press Confirm to read the message. You can choose the following options:
 - Send form SIM1: you can send the message form SIM1 to more than one recipient by choosing sending to multiple recipients or group.

- Send form SIM2: you can send the message form SIM2 to more than one recipient by choosing sending to multiple recipients or group
 - Edit: edit the message.
 - Delete: delete the message.
 - Copy to SIM Card (Copy to Phone): copy the message from the phone to the SIM card, or vice versa.
 - Move to SIM Card (Move to Phone): move the message from the phone to the SIM card, or vice versa.
 - Delete All: delete all the message in the outbox.
 - Copy All: copy all from SIM card to the phone or from the phone to SIM
 - Move All: move all from SIM card to the phone or from the phone to SIM
 - Use Number: dial or store in the phonebook the number extracted from the message
 - Use Link: Extract and store the web link contained in the message
 - Write message: Enter in to write message. You can enter short message.
 - Complete: select the entry to stand for finishing keying message and you can take the next steps.
1. Send only: to send the message, select to get into recipients and you can enter the phone number or look from the phonebook and select the receiver's phone number. Enter confirm to send.

2. Send and save: while sending the message, it automatically saved into the outbox.
 3. Save: not send the message but only save it into the outbox.
 4. Send to many: send the message to several phone numbers.
 5. Send in group: select a group and the send the message to all the members in the group.
- use templates: insert the text template into the message.
 - Insert object: insert pictures, ring tone, cartoon and default music to the message.
 - Text format: define the text editing format.
 - Insert number: add numbers from the phonebook.
 - Insert contact: add names from the phonebook
 - Input method: change the input method.

*Note: some of the cities and district message centers do not support message over than 70 characters (or 160 English texts).

- Templates: frequent used sentences could be saved here to avoid rewrite it during message editing. It is editable and could be deleted.
- Message setting: before using message function, you need to do necessary settings.

- Profile settings: set a proper mode for mobile message. Enter into each mode to find the matching name, message centre number, validate time, sending profile setting.
- Common settings: activate Reports or Reply Path.
- Memory status: check the available space in SIM card or mobile message box.
- Preferred storage: choose to save in mobile or SIM card.

◆ MMS

Multimedia messages contain text, picture and sound. Through MMS (Multimedia Messaging Service), you can not only send or receive pictures and texts, but also receive audio files attached to messages.

The phone supports multimedia messages with multiple pages, i.e. each page consists of one picture, one piece of music and text. A multimedia message contains several such pages. Size of pictures in the multimedia messages will be automatically adjusted to the screen of the phone.

* Note: This function requires the support of the network supplier.

- Write a Message: create a new multimedia message. You need to fill in the recipient, copy, confidential copy, subject content and attachment.
- Inbox: read the multimedia messages received. (Similar to the inbox of text messages.)
 - Read: read the multimedia message.
 - Details: check the detail of the multimedia message, including the addresser, subject, date, time and size.]]

- Use number: extract the sender's number.
- Reply: reply in multimedia format to the sender of the multimedia message or all the senders and recipients
- Reply: reply in text message to the sender of the multimedia message or all the senders and recipients
 - Forward: forward the multimedia message to others.
 - Receive: if the multimedia message is not received, receive it.
 - Disconnect: Disconnect with GPRS.
 - Delete: delete the multimedia message.
 - Delete All: delete all the multimedia messages in the inbox.
- Outbox: store the multimedia messages sent unsuccessfully.
- Drafts: store the multimedia message not intended to send.
- Templates: frequent used sentences could be saved here to avoid rewrite it during message editing. It is editable and could be deleted.
- MMS Setting: set the parameters of sending and receiving the multimedia message.
- Profiles Setting: MMS setting, including the settings of MMS center, linking type, gateway, port and account.

*Note: MMS setting needs to set according to the local network supplier's standard, such as linking type select as WAP or HTTP.

- Edit Setting: set the parameters of editing multimedia message, such as edit mode, Picture Zoom Out, signature and so on.
- Send Setting: set the parameters of sending the multimedia message, such as Period Validity, Sent Report, Read Report, Priority, intermission time and

Sent Time

- **Receive Setting:** set the parameters of receiving the multimedia message, such as main network, roaming network, send report, read report and permit sending report and so on.
- **Filter:** filter the multimedia messages.
- **Memory:** space of the saved multimedia messages, used memory and free memory.

◆ Chat

Functions of the chat room are as follows:

- **Chat Room info:** input a nickname and the number of your partner.
- **Start new:** input message to start chatting with the partner.

◆ Voicemail server

Functions of the voice mailbox are as follows:

- **Edit:** you can set the name and phone number.
- **Connect to the Voice Mailbox:** dial the voice mailbox you set to listen to the voice message.

◆ Broadcast message

Functions of receiving and reading the messages of cell broadcast are as follows:

- **Receiving Mode:** open or close the receiving of cell broadcast message.
- **Read Message:** read the cell broadcast messages you subscribe to.
- **Language:** set the language of cell broadcast.
- **Channel Setting:** set the channel of cell broadcast, including the selection,

add, edit and delete.

3.3 Call center

◆ Call history

You can select SIM1 call history, or SIM2 call history, the menu as follows :

- Missed Calls: to take the record of 20 missed calls.
- Dialed Calls: to take the record of 20 dialed calls.
- Received Calls: to take the record of 20 received calls.

In the list of Logs, press Ok to check the detail of the entry, such as the date, time, name (if recorded in the phonebook) number and times of calling.

In Detail of the entry, press Option for the following operations:

- IP Dial-up: activate the IP dial-up of numbers in the record
- Send message: send message to the number
- Send MMS: send mms message to the number
- Delete all: Delete all the record
- Delete: delete the entry.
- Save: save the entry in the SIM card or the phone.
- Dial: dial the entry.
- Edit: edit the entry and add it into the phonebook.
- Delete Log: The user can choose to clear all the entries of a list.
- Call Duration: Four sub-menus are provided in Call Duration: Last Call, Dialed Calls, Received Calls and Clear All.
 - Last Call: check the duration of the last call.
 - Dialed Calls: check the total duration of dialed calls.
 - Received Calls: check the total duration of received calls.
 - Clear All: clear the timer and restart counting.
- Call time: The Call Meters can keep the record of your total call charge.

- Last Call Charge: Check the last call charge.
- All Call Charges: Check the total call charge.
- Reset Call Meter: Enter PIN2 code to reset the call meter.
- Charge Limitation: Enter into this sub-menu and key in the PIN2 code to browse, edit or deactivate the function.
- Price and Rate: Enter into this sub-menu to browse, edit or deactivate the function, the latter two functions need the input of PIN2 code.

*Note: Some operations require the PIN2 code; please contact your network supplier for it.

*Note: Network support is needed.

➤ Message Counter

- Sent: record the number of sent messages.
- Received: record the number of received messages.

Press the Left Soft Key of "reset" to clear the above two items.

➤ GPRS counter

- Last Sent: record the bytes sent last time.
- Last received: record the bytes received last time.
- All Sent Data: record all the bytes sent.
- All Received Data: record all the bytes received.

- Clear Counters: start counting

◆ Call Settings

➤ SIM1 call settings

1▣ Caller ID

- Default: sending of your phone number in the default setting.

- Hide: the other side cannot see your phone number during the calling. (Require the support of the network supplier.)
 - Send: the other side can see your phone number during the calling.
- 2] Call Waiting: You can activate it to be notified of incoming calls while you have a call in progress.

3] Call Diversion:

- Unconditional: divert incoming calls to another number unconditionally.
- If Out of Reach: divert incoming calls to another number if you cannot be reached.
- If Not Answered: divert incoming calls to another number after you phone rings for a specified time without answering.
- If Busy: divert incoming calls to another number when you have an active call.
- All Data Calls: divert data calls.
- Cancel Diversion: cancel the diversion of calls.

4] Call Barring: to restrict calls

- Outgoing Calls: restrict the making of calls.
- Restrict Incoming Calls: restrict the receiving of calls
- Cancel Barring: cancel the restriction. (Need PIN2 code.)
- Change Password: change the password

5] Line Switch: Switch between line 1 and line 2. (Note: when line 2 is chosen, no calls can be made.)

6] closed user group] Enter and select "add" to input the group name. use touching pen to select finish the edit. After that, enter content number and select confirm by touching pen. Select the existing group to edit, add, active, inactive and delete. To shut down the group setting is determined by network supplier. only the group member could call each other to limit the calling cost.

*Note: the function needs the support of network supplier of the SIM card.

➤ SIM2 call settings

The same to the SIM1 call settings.

➤ Pitch Shift

You can open and close the pitch shift when calling.

- Close :Close the pitch shift,you can keep the voice to normal when you calling.

➤ Open:Choice the voice of the Child,Girl,Woman,Ms.,Boy,Man,Tedious and Hoarse.If you open the function,you can used the voice of you setting when Calling.

➤ Advance setting

1] Black list] you can edit the phone number in the restricted call lista and choose to turn on or off the function. If set on, the phone number in the list would be rejected to be connected.

2] Automatic Redial: Have your phone redial a number after it fails doing so

3] Speed dial: In standby, press and hold corresponding numeric keys to dial the number set for them.

4] IP Dial-up: to set and store the IP dial-up of numbers in the phonebook

5] Call time display: Display the duration of a call at the end of a minute

6] Call time reminder: display the duration of a call

7] Auto quick end:end the call at the setting time.

3.4Settings

◆ Dual SIM settings

Dual SIM open:open the dual SIM

Only SIM1 open:only open the SIM1

Only SIM2 open:only open the SIM2

Flight mode:close the network,open flight.

◆ Pen calibration

You can use touchscreen to re-calibration.

◆ Phone Setup

- Time and Date: set time and date of the phone.
- Set home city: Set the city of you seat.
- Time/ Date Setting: set the current time and date.
- Time Format: set the display format of time.
- Schedule power on/off: set the time when the phone is turned on and off automatically.
- Language: set the language for the menu
- Preferred Input Method: select a default input method.
- Display characteristic:
 - Wallpaper: select the wallpaper for standby.
 - Screen saver: select a screen saving picture for standby and set the waiting time.
 - Power on display: select the film played when the phone is turned on.
 - Power off display: select the film played when the phone is turned off.
 - Date and Time Display: Open or close the display of the current time in standby.
- Greetings text: When Greetings is activated, an edited message will be displayed when the phone is turned on.
- Auto update of data and time: Open and close the auto update of data and time.

- Handwriting setting: set the handwrite speed and the writing color.
- Misc. settings:
 - LCD Backlight: set mobile LCD backlight brightness and time.
 - Keypad LED: Open and close the color LED.
 - Keypad LED Style: setting the LED styles.
- ◆ Call Settings
 - SIM1 call settings
 - 1) Caller ID
 - Default: sending of your phone number in the default setting.
 - Hide: the other side cannot see your phone number during the calling. (Require the support of the network supplier.)
 - Send: the other side can see your phone number during the calling.
 - 2) Call Waiting: You can activate it to be notified of incoming calls while you have a call in progress.
 - 3) Call Diversion:
 - Unconditional: divert incoming calls to another number unconditionally.
 - If Out of Reach: divert incoming calls to another number if you cannot be reached.
 - If Not Answered: divert incoming calls to another number after you phone rings for a specified time without answering.
 - If Busy: divert incoming calls to another number when you have an active call.
 - All Data Calls: divert data calls.
 - Cancel Diversion: cancel the diversion of calls.
 - 4) Call Barring: to restrict calls
 - Outgoing Calls: restrict the making of calls.
 - Restrict Incoming Calls: restrict the receiving of calls
 - Cancel Barring: cancel the restriction. (Need PIN2 code.)

- Change Password: change the password

5] Line Switch: Switch between line 1 and line 2. (Note: when line 2 is chosen, no calls can be made.)

6] Shut down group] Enter and select "add" to input the group name. Use touching pen to select finish the edit. After that, enter content number and select confirm by touching pen. Select the existing group to edit, add, active, inactive and delete. To shut down the group setting is determined by network supplier. Only the group member could call each other to limit the calling cost.

*Note: the function needs the support of network supplier of the SIM card.

➤ SIM2 call settings

The same to the SIM1 call settings.

➤ Pitch Shift

You can open and close the pitch shift when calling.

- Close :Close the pitch shift, you can keep the voice to normal when you calling.

➤ Open: Choose the voice of the Child, Girl, Woman, Ms., Boy, Man, Tedious and Hoarse. If you open the function, you can use the voice of your setting when calling.

➤ Advance setting

1] Black list] you can edit the phone number in the restricted call list and choose to turn on or off the function. If set on, the phone number in the list would be rejected to be connected.

2] Automatic Redial: Have your phone redial a number after it fails doing so

3] Speed dial: In standby, press and hold corresponding numeric keys to dial the number set for them.

- 4] IP Dial-up: to set and store the IP dial-up of numbers in the phonebook
- 5] Call time display: Display the duration of a call at the end of a minute
- 6] Call time reminder: display the duration of a call
- 7] Auto quick end: end the call at the setting time.

◆ Network setup

Show SIM1 network settings and SIM2 network settings.

➤ Network Selection:

- Automatic: search automatically for the network to which the SIM card belongs to.
- Manual: search for all available networks and register manually.

➤ Preferred Network: pre-store your preferred networks

◆ Security setup

➤ SIM security setup

1] SIM1 Lock:

You can make the security settings to prevent your phone or SIM card from unapproved use.

The PIN code can prevent your SIM card from unapproved use. If the PIN code is closed, you can open it to activate its protection. The phone will ask for the PIN code next time the phone is turned on. If the PIN code is opened, you can close it to deactivate its protection. You can also change the PIN code by following the screen indication: input the previous PIN code, input the new PIN code and input again.

*Note: The SIM card will be locked if the inputs of PIN codes are wrong for three times. Then you need the PUK code to unlock the SIM card. The PIN code and PUK code are supplied together. If not, please contact your network

supplier. The default PIN code is 1234; please change it into your personalized password.

2] Fixed Dial: If activated, only the numbers set in the list or numbers started with the digits in the list can be made. (Require the support of SIM card.)

- Mode: open or close the function of Fixed Calls. (Need to input PIN2 code.)
- Fixed Calls List: input the fixed phone numbers into the list.

*Note: Open or close the function of Fixed Calls requires the input of PIN2 code. Please contact your network supplier for the PIN2 code. Enter Fix Calls; numbers of fixed calls will appear in the directory.

3] Barred Dial: Contrary to Fixed Calls, you can restrict the calling of certain numbers.

4] Change Password: change the passwords of PIN code, PIN2 code and the phone.

*Note: Certain functions are network service.

➤ SIM2 security setup

The same to the SIM1 security setup.

➤ Phone Lock:

The phone lock can prevent your phone from unapproved use. Select Phone Lock to activate the protection of your phone. The phone will ask for the password next time it is turned on; press again to deactivate the protection.

- Use the Right Soft Key to clear a wrong input when entering the password and press OK to confirm.

For example, if the password is set as 1122, enter: 1122.

*Note: The default password of the phone lock is 1122; please change it into

your personalized password. If you forgot the password of your phone, you would have to contact the distributor or the local service center to unlock your phone

➤ Auto Keypad Lock:

- the keypad will lock itself after the phone is unused for a specified time you set.

- Open Keypad lock in standby: press the send key to unlock the keypad.

◆ Restore factory Settings

Reset to default settings with the password of 1122.

◆ Sound Effect

Set the sound effect of audio player: Equalizer| Reverb| 3D surround effect

3.5 Multimedia

◆ Mobile TV

TV function. Use manual or automatic search to obtain the channel.

*Note: the function need to select the relative channel setting and get better TV signal by adjusting the antenna.

➤ joined my channel: Custom channel options| Can be used or their favorite channels saved to my list of channels. To facilitate the broadcast channel at the choice.

➤ My channel| My channel list, Can be used to preserve the added channel.

➤ Select area: provide different area setting for selection

➤ Auto Searcher: Can auto search channel. The signal channel will be saved to the list of channels. You can choice of channel.

➤ Channel list: saver the obtained TV channel into the list.

- Loud Speaker: open or close Loud Speaker.
- display settings
 - Brightness: Adjust the brightness of television
 - Signal strength display: open or close the signal strength display.
 - Weak signal display: open or closed Weak signal display.

◆ Camera

The phone is equipped with a camera. Enter into Camera and press ok to start photo taking. Options are as follows:

- photos: enter into Album.
- Camera Settings: set the relevant parameters of photo taking
- Image Settings: set the size and quality of photos.
- White Balance: set the color of the light.
- Scene mode: set the mode of automatic or night shooting.
- Effects settings: choose the display style.
- Add Frame: choose the frame for the picture
- Storage: save the picture in the phone or the memory card.
- Restore default: reset to default setting

◆ Image viewer

Store the pictures taken by the camera.

- View: zoom in the selected picture.
- Browse style: change the mode of picture browse. "Matrix" and "List" are available.
- Forward: use the selected pictures as the wallpaper, screen saver, switch on/off film, and adding to the phonebook.
- Rename: rename the selected picture.
- Delete: delete the selected picture.

- Delete All files: delete all the pictures in the album.
- Sort by: sort the pictures of the selected folder by name, type, date or size.
- Storage: change or choose a default storage path for the pictures.

◆ Video recorder

The phone is equipped with a film recorder. Enter into Film Recorder and press ok to start film recording.

Options are as follows

- To player: enter into film player and play the film recorded
- Camcorder Settings: set the relevant parameters of the recorder
- Video Settings: set the size, format, recording time, quality and sound effect of films.
- Effects settings: choose a special effect for the recording.
- Storage : save the picture in the phone or the memory card.
- Restore default : reset to default setting

◆ Video player

Play the films stored by users. Options are as follows:

- Play: play the selected file.
- Forward: transfer the selected file to the phonebook, screen saver, and switch on /off film.
- Rename: rename the selected file.
- Delete: delete the selected file.
- Delete All files: delete all the files.
- Sort by: arrange the files in terms of name, type, date, size or none).
- Storage: check the location of the file (in the phone and the memory card).

◆ Audio player

Select Music Player to enter into the Audio Player.

- Play: play the selected file.
- Details: check the details of the song
- Add to the Ring: add the song into the ring library of profiles.
- Refresh list: update the playlists.
- Settings: set the playing of multimedia files.
 - Playlist Location: set the default reading path.
 - Create the list automatically: whether to update the playlists every time the phone is turned on or not.
 - Repeat: repeat the playing.
 - Random: play randomly.
 - Background playing: playing will not stop when exiting the menu.
 - Sound Effects: Set the sound effect of audio player.
 - Spectrum display: choose the spectrum for the player.
 - BT stereo output: On and off the BT stereo output
 - BT stereo output headset: Select the BT stereo headset.

In standby, I key and O key adjust the volume of keypad tones.

During a call, I key and O key adjust the volume of the receiver.

In the mode of music player, I key and O key adjust the volume of the player.

◆ Record

Choose to record. Touch left soft key to do the operations:

- Record: record a new sound
- Play: play the selected recorder
- Append:: add new recorder to the original recorder. (only for AMR format)
- Rename: rename the recorder
- Delete: delete the current recorder
- Delete all files: delete all the recorders
- Setting: set the recorder's format

- Forward: send the recorder to profiles or sendy by multimedia message.

◆ FM Radio

the phone supports FM broadcast. Select the FM shortcut to to the relative actions. Press select key to do the following actions:

- Channel list" edit the name of the channel and display in the list
- Manual Input: direct input FM channel frequency, eg 103.7
- Preset auto search: automaticly search FM channel and updated the list.
- Settings: background play, FM speaker play.
- Record: record a new audio
- Append: add a new record to the original one.
- File list:the record files.

3.6File manager

- Functions:
 - Open: display the contents of the folder.
 - Create: create a new archive under the current folder.
 - Format: format the folder.
 - Rename: rename the files or folders.
 - Delete: delete the files or folders.
 - Sort: sort the files or folders.
 - Details: check the details of the files or folders.
 - Copy: copy the files or folders to any position.
 - Move: move the files or folders to any position.
 - Delete All: delete all the files or folders of the current folder.
- Folder
 - Audio: the default storage path of audio.
 - Images: the default storage path of images.

- My Music: the folder for uploaded audio files and the default reading path of the audio player.
- Photos: the default storage path of photos.
- Video: the default storage path of videos.

3.7 Fun & Games

◆ Java

The J2ME java applications.

◆ Game

➤ Majungl

- New game: start a new game.
- Game mode: select the game level.
- Best grades: record the player's playing record.
- Help: get to see the game rules.
- Magic sushi (specified menu operation same as above)
- Game setting
 - BGM: turn on/off the background music
 - Sound effect: turn on/off the sound effect
 - Games vibration: turn on/off the games vibration.

3.8 User Profiles

◆ General

➤ Activate: activate the general profile

➤ Personalize: Enter into individual settings of the general profile. Functions as follows:

- Ring Tone settings: change the ring tone for incoming calls, alarm clock, phone on/off, phone sliding, message and keypad tone.
- Ring volume: adjust the volume of ring tone and keypad tone.
- Ring Type: ring, vibration, vibration and ring, ring after vibration.
- Incoming Call Alert: ring once, ringing or ascending.
- Message Alert Tone: set the alert tones for warning, error, network connection or call connection.
- Answering Mode: set any key to answer an incoming call

◆ Meeting

The same as the general profile.

◆ Outdoor

The same as the general profile.

◆ Indoor

The same as the general profile.

◆ Earphone

Automatically activate the profile when earphone is plugged in. The rest is the same as the general profile.

◆ Bluetooth

The same as the general profile

3.9 Organizer

◆ Calendar

Enter into the sub-menus of Calendar.

- Calendar: create a new event and add an alarm clock to it by Once, Daily, User-defined, Weekly, and Monthly.
 - Once: the event will warn only once.
 - Daily: the event will warn at the specified time every day.
 - User-Defined: the event will warn at a time of the week defined by the user.
 - Weekly: the event will warn at the specified time every week.
 - Monthly: the event will warn at the specified time every month.
- Jump to Specified Date: jump from the current date to the specified date.
- Lunar Calendar: open or close the lunar calendar.

*Note: Due to the memory limit, stored entries should not exceed 70; otherwise entries may be missing

◆ To do list

- Add
 - Date: the date of a memo entry.
 - Time: the time of a memo entry.
 - Remark: the message shown on the screen when warning.
 - Alarm Clock: open or close the alarm clock.
 - Mode:
 1. Once: warn only once.
 2. Daily: warn at the specified time every day.
 3. User-Defined: set the warning time of the alarm clock in a week.
 4. Weekly: warn only once in a week.
 5. Monthly: warn only once in a month.
- Browse: check the stored entries.
- Add: add a new entry
- Edit: edit the stored entries.
- Delete: delete a selected entry.
- Delete All: delete all the entries.

➤ Transfer: transfer the selected entry to another phone by messaging, or store it in the archives of the phone.

◆ Alarm

➤ On/Off: open or close the alarm clock.

➤ Time: set the alarm time

➤ Mode:

- Once: warn only once.

- Daily: warn at the specified time every day.

- User-Defined: set the warning time of the alarm clock in a week.

➤ Ring setting

Choose melody or saved FM record as the ring tone

➤ Snooze time (minute)

Choose to snooze every few minutes. There are 11 options such as every 1 min to every 10 min and default.

➤ Ring method: the option ring tones are ring, vibration, vibration and ring.

◆ World clock

Use direction key to read each city's time zone and the date and time in each city.

3.10 Services

◆ WAP

➤ Menu function:

➤ Homepage: log on to the homepage. The homepage is a WAP site you set in the connecting settings. If you haven't set it, it will use the one set by the

manufacturer.

- Bookmark: display the bookmarks available. Select it to connect to the website.
- History: keep the websites you surfed on record.
- Enter Address: enter any WAP website or other internet websites.
- Setting: make the setting of websites browsing.
- Edit Setting Profile: select the Setting Profile among the 10 options provided.
- Browsing Properties: parameter settings of browsing websites, including standby time and picture display.
- Service Message: open or close service message.
- Clear Buffer Memory: clear the buffer memory.
- Clear Personal Information: clear your personal information.
- Clear History: clear the history.
- Certificate: check the certificates.
- Online functions
 - Jump to: jump to the directed address.
 - Right Soft Key (Back): back to the previous page
 - Homepage: back to the homepage
 - Refresh: refresh the page
 - Bookmark: display the bookmarks available. Select it to connect to the website, edit the addresses or names of bookmarks or delete the bookmarks.
 - History: check the websites you surfed on the record

- Enter Address: enter directly the URL to go to the website
- Set as Homepage: set the current page as the homepage
- Save Picture: save the picture of the current page.
- Service Inbox: check the service inbox for messages.
- Settings: enter into the setting menu.
- Exit: exit the WAP explorer and back to the main menu.

*Note: GPRS service requires the support of the network and is only available after the service is put into operation.

◆ Account information

➤ GSM Data

- Name: the name of the account. You can edit it.
- Number: the number of the account.
- User's Account: the account number of dialing server (not WAP gateway).
- Password: the password of dialing server (not WAP gateway).
- Line Type: analog line or digital line.
- Speed: select the proper transfer speed.
- Network Domain: IP address

➤ GPRS

- Name: the name of the account. You can edit it.
- GPRS Connect Node: enter APN.
- User's Account: the account number of dialing server (not WAP gateway).
- Password: the password of dialing server (not WAP gateway).
- Certification: choose the encryption method of the certification.

➤ Wireless LAN:

- Enable WLAN: Enable and disable the WLAN
- WLAN status: Show the WLAN status.

Such as: device address, SSID, BSSID, Channel, Signal strength, Link speed, IP address and so on.

- Access point settings
- 1.connect:Connect and disconnect the AP

2.Edit:Edit the AP settings.

Such as: SSID,Network,TCP/IP,Security mode,Encryption mode.

3.New access point:set up the access point

4.Delete>Delete access point.

5.change priority:change the priority.

- Search for networks:Search the available networks.

1.connect:Connect and disconnect the AP

2.Define access point: Define the AP settings.

3.Details>Show the AP details

4.Refresh:Refresh the available networks list.

◆ STK

STK is the additional service provided by network supplier. the function menu is different from each SIM card.

3.11Extra

◆ Calculator

- Press the key 0-9 for the input of numbers and the # key for that of the decimal point.
- Press the key up, down, left and right for the input of the mathematical symbol of +[] -[] x[] ÷.
- Press the Right Soft Key to clear the last entry. Press the Right Soft Key to

“Exit” calculator; and press the Left Soft Key to “Get” the result.

*Note: the precision of the calculator is limited. There may be rounding errors, especially when a number can not be divided

◆ Unit Converter

➤ Weight: include conversion between kilogram <|> pound and kilogram <|> ounce. Input the number into the corresponding field, press the Left Soft Key to confirm. The result will show up in the other field.

➤ Length: include conversion between kilometer <|> mile, meter <|> yard, meter <|> foot and centimeter <|> inch. Input the number into the corresponding field, press the Left Soft Key to confirm. The result will show up in the other field.

◆ Currency Converter

Carry out the conversion among any currency. You need to input the exchange rate first then the amount of the domestic currency or that of the foreign currency, and press the Left Soft Key to confirm. The result will show up in the other field

◆ Health

➤ Index of Physical Quality

Enter and choose male or female; enter the height and weight and press OK. The result will be shown in a diagram indicating the range of the index of your physical quality.

◆ Stopwatch

- Calculate the time which is taken.

◆ E-Book reader

➤ Open ebook: Open the ebook file.

➤ Cleanup bookshelf| Update the ebook list.

➤ Settings

- Font style: Select the font style for Normal, Italic and Bold.
- Scroll By: Select the scroll by page and line.
- Auto scroll: Open and close the auto scroll.
- Scroll speed: Select the auto scroll speed.
- Full screen: Open and chose the full screen mode.
- Encoding format: Select the ebook encoding.
- Memory: Select the memory to the memory card or phone.
- Info: Show the ebook information.
- Delete: Delete the ebook file.
- Delete all: Delete all the ebook in list.
- Default settings: Restore the default settings.
- Help: The help info.

◆ Bluetooth

The phone is equipped with the Bluetooth technology, and supporting ear bud mode, text transferring mode and other modes. Bluetooth menu settings as follows:

- Activate: open or close Bluetooth.
- Search for hands-Free Device: search for the current Bluetooth hands-free devices.
- My device: the list of devices being connected.

- Device in Connection: devices being connected.
- Settings: include the settings, such as searchable setting, file transfer setting
- My Bluetooth: check the status of the Bluetooth.

Establish a Bluetooth connection

Activate the Bluetooth, select "Search for Hands-Free Device", or enter into "My Device" → "Option" → "Search for New Device" to search for the Bluetooth device within the effective range. Enter the agreed password to establish a match between devices before data transfer.

After connecting with the Bluetooth, the following functions are applicable to the connected devices.

- Connecting: obtain the information resources from the connecting devices.
- Device Name: change the device name of the other side.
- Delete: delete the name of a selected device.
- Delete All: delete all the records in the device list.
- Service Record: check the service available.
- Searching for new device: search for new devices within the effective range.

*Note:1.By using the Bluetooth technology, the phone can get in connection with devices compatible with Bluetooth within 10 meters. However, the connection may be affected by barriers like wall or other electronic devices.

2.The use of Bluetooth may accelerate the consumption of battery power

and shorten the battery life. It is advisable to turn Bluetooth off when not needed.

3.To ensure a smooth connection between the phone and other wireless technology supported devices, please use the accessory authorized by the device manufacturer. Please make sure with the manufacture if the device is compatible with the phone .

3.12Shortcuts

The phone provides 11 shortcuts. Open the menu and select the shortcuts function to get into the shortcut

CHAPTER 4 Troubleshooting

Settings of certain functions fail	Such functions are not supported by the network supplier or you haven't applied for them.
PIN locked	Enter the password and PUK code supplied with the SIM card or contact the network supplier.
PIN2 locked	Enter the password and PUK2 code supplied with the SIM card or contact the network supplier.
Call meter invalid	The data transfer counter doesn't work; please contact your network

	supplier.
SIM card errors	<ol style="list-style-type: none">1. The SIM card is dirty, clean it.2. Reinstall the SIM card3. The SIM card is damaged, change one.

The Manufacture reserves the ultimate right for the interpretation of this manual.

The Manufacture reserves the right for the changes in the technical standards without advanced notice.

The Manufacture reserves the right for the changes in this manual without further notice.

The Manufacture reserves the right for the changes in the technical specification without advanced notice.

■ Certification information (SAR)

This mobile device meets guidelines for exposure to radio waves. Your mobile device is a radio transmitter and receiver. It is designed not to exceed the limits for exposure to radio waves recommended by international guidelines. These guidelines were developed by the independent scientific organization ICNIRP and include safety margins designed to assure the protection of all persons, regardless of age and health.

The exposure guidelines for mobile devices employ a unit of Measurement known as the Specific Absorption Rate or SAR. The

SAR limit stated in the ICNIRP guidelines is 0.43 watts/kilogram

(W/kg) averaged over 10 grams of tissue. That amount changes depending on a number of factors such as how close you are to a network base station. The SAR value under the ICNIRP guidelines for use of the device at the ear

is 0.49 W/kg.